

## Contents

- [1 General Incompatibility Information](#)
- [2 List of Incompatible Devices](#)

## General Incompatibility Information

There are various points where you can see if your device **will not** be supported even if your router isn't listed here!

A router can not be supported by dd-wrt if:

- it is based on a Texas Instruments (TI) chipset
- it is based on a Marvell chipset (maybe in the future?)
- it is based on a Uvicom chipset
- it is based on a Realtek chipset
- it is based on a Broadcom 63xx chipset
- it is based on a Trendchip chipset
- it has <2MB flash
- it has <4MB flash and is NOT Broadcom (any other supported vendor) based
- it has <16MB RAM and is NOT Broadcom (any other supported vendor) based
- it has an integrated modem (dd-wrt is router firmware and does not support the modem part)
- it has VOIP ports (RJ-9)

## List of Incompatible Devices

These devices were tested with DD-WRT, but the tests failed, or their specs make them incompatible even without testing. If you bricked your router, please first consult the [support](#) page. After developers confirm the incompatibility with DD-WRT, please edit this page.

Only add devices that cannot be supported, **not** devices that will be supported in the future or are WIP!

Brand	Model Number	Hardware revision	FCC-ID	Additional notes
Airlink 101	AR315W	-	MQ4ARM914	Marvell MV88W8510 SOC 1MB Flash/4MB RAM
Airlink 101	AR525W	v1	MXF-R940711G	RDC3211-G CPU 4MB Flash/16MB RAM
Airlink 101	AR625W	v1	-	Marvell MV88F5180 SOC 8MB Flash/32MB RAM
Airlink 101	AR675W	v1	NDD9564280906	Realtek RTL8196B SOC 2MB Flash/16MB RAM
Airlink 101	AR680W	v1	RRK-AR680W	Ralink RT1310 CPU 4MB Flash/16MB RAM

Known\_incompatible\_devices

Airnet	AWR014G8	v1	NHPWLG2207	Atheros AR2312A CPU 1MB Flash/8MB RAM
Aopen	AOI-893	?	?	Marvell Chipset 16MB RAM
Asus	WL-330G	v1	MSQWL330G	Marvell MV88W8510 SOC 1MB Flash/8MB RAM
Asus	WL-566GM		MSQWL566GM	Realtek RTL8651B SOC 4MB Flash/32MB RAM
Asus	RT-N10	E	MSQRTN10E	Realtek RTL8196C SOC 4MB Flash/16MB RAM
Asus	RT-N11		MSQRTN11	AMRISC 20010 CPU 2MB Flash/8MB RAM
Asus	RT-N12E	E	MSQRTN12E	Realtek RTL8196C SOC 4MB Flash/16MB RAM
Asus	RT-N12LX	E	MSQRTN12E	Realtek RTL8196C SOC 4MB Flash/16MB RAM
Ativa	AWGR54	v1000	RAXWG4005G	Atheros AR2317 SOC 2MB Flash/8MB RAM
Belkin	F5D7230-4	v4xxx	K7SF5D7230A	Marvell MV88W8510 SOC 1MB Flash/4MB RAM
Belkin	F5D7230-4	v6xxx	K7SF5D7230C	Marvell MV88W8510 SOC 1MB Flash/8MB RAM
Belkin	F5D7230-4	v7xxx	RAXWG4005G	Atheros AR2317 SOC 2MB Flash/8MB RAM.
Belkin	F5D7230-4	v8xxx	K7SF5D7230D	Broadcom BCM5354 SOC 1MB Flash/8MB RAM
Belkin	F5D7230-4	v9xxx	K7SF5D7230E	Realtek RTL8186 SOC 2MB Flash/8MB RAM
Belkin	F5D7230-4	vAxxx	K7SF5D7230F	Atheros AR2317 SOC 2MB Flash/8MB RAM
Belkin	F5D7234-4	v3xxx	K7SF5D7234v3	Atheros AR2317 SOC 2MB Flash/8MB RAM
Belkin	F5D7234-4	v4xxx	K7SF5D7234v4	Atheros AR2317 SOC 2MB Flash/8MB RAM
Belkin	F5D7234-4	v5xxx	K7SF5D7234v5	Broadcom BCM5355 SOC 2MB Flash/8MB RAM
Belkin	F5D7632-4	v1xxx	K7SF5D7632-4	Modem/Router combo
Belkin	F5D8230-4	v2xxx	SA3-AGN0901AP0100 SA3-AGN1223AR0300	Realtek RTL8651B SOC 4MB Flash/16MB RAM
Belkin	F5D8233-4	v1xxx	K7SF5D8233-4	Infineon PSB50610 CPU 4MB Flash/16MB RAM
Belkin	F5D8233-4	v3xxx	K7SF5D82334C	Ralink RT2880 CPU 2MB Flash/16MB RAM
Belkin	F5D8236-4	v1xxx	K7SF5D8236A	Ralink RT2880F CPU 2MB Flash/16MB RAM
Belkin	F5D8236-4	v2xxx	K7SF5D8236V2	

Known\_incompatible\_devices

				Ralink RT3052 SOC 2MB Flash/16MB RAM
Belkin	F5D8236-4	v3xxx	K7SF5D8236V3	Ralink RT3052 SOC 2MB Flash/8MB RAM
Belkin	F5D8635	v1, v2	K7SF5D8635	Modem/Router combo
Belkin	F5D9230-4	v4	K7SF5D9230-4V4	AMRISC 10000-G CPU 1MB Flash/2MB RAM
Belkin	F6D4230	v1	K7SF6D4230V1	Ralink RT3050 SOC 2MB Flash/8MB RAM
Belkin	F6D4230	v2	K7SF6D4230V2	Ralink RT3050 SOC 2MB Flash/8MB RAM
Belkin	F6D4230	v3	K7SF6D4230V3	Broadcom BCM5356 SOC 2MB Flash/8MB RAM
Belkin	F7D1301	v1	K7SF7D1301V1	Broadcom BCM5356 SOC 2MB Flash/8MB Ram
Belkin	F7D2301	v1	K7SF7D2301V1	Ralink RT3052 SOC 2MB Flash/8MB RAM
Belkin	F7D3401	v1	K7SF7D3401V1	Modem/Router combo
Belkin	F7D3402	v1	K7SF7D3402V1	Modem/Router combo
Belkin	F7D4401	v1	K7SF7D4401V1	Modem/Router combo
Belkin	F7D4402	v1	K7SF7D4402V1	Modem/Router combo
Belkin	F7D5301	v1	K7SF7D5301V1	Broadcom BCM5356 SOC 2MB Flash/8MB RAM
Belkin	F7D5301	v3	K7SF7D5301V3	Realtek RTL8196C SOC
Belkin	F7D6301	v1	K7SF7D2301V1	Ralink RT3052 SOC 2MB Flash/8MB RAM
Belkin	F7D6301	v3	K7SF7D6301V3	Realtek RTL8196C SOC
Belkin	F9K1001	v1	K7SF9K1001V1	Realtek RTL8196C SOC 2MB Flash/8MB RAM
Belkin	F9K1001	v3	K7SF9K1001V3	Realtek RTL8196C SOC 2MB Flash/8MB RAM
Belkin	F9K1002	v1	K7SF9K1002V1	Realtek RTL8196C SOC 2MB Flash/8MB RAM
Belkin	F9K1002	v2	K7SF9K1002V2	Ralink RT3052 SOC 2MB Flash/8MB RAM
Belkin	F9K1002	v3	K7SF9K1002V3	Realtek RTL8196C SOC 2MB Flash/8MB RAM
Belkin	F9K1116	v1	K7SF9K1116V1	Realtek RTL8197D SOC 8MB Flash/64MB RAM
Buffalo	WZR2-G300N	v1	FDI-09101485-0	Ralink RT1310 CPU 4MB Flash/16MB RAM
D-Link	DAP-1360	A1	KA2AP1360A1	Realtek RTL8651C SOC
D-Link	DAP-1360	B1	KA2AP1360B1	Realtek RTL8196B SOC
D-Link	DAP-1360	C1	KA2AP1360C1	Realtek RTL8196C SOC 4MB Flash/32MB RAM

Known\_incompatible\_devices

D-Link	DI-524	A1	KA2DI524	Marvell MV88W8510 SOC 2MB Flash/8MB RAM
D-Link	DI-524	A2	KA2DI524A2	Marvell MV88W8510 SOC 2MB Flash/8MB RAM
D-Link	DI-524	C1	KA2DI524C1	Atheros AR2313A CPU 1MB Flash/8MB RAM
D-Link	DI-614+	A1/A2	KA2DI614-PLUS (invalid FCC id)	Samsung S3C4510B CPU 1MB FLASH/8MB RAM
D-Link	DI-624	C2	KA2DI624VC2	Atheros AR2312A CPU 1MB Flash/8MB RAM
D-Link	DI-724GU	A3	KA2DI724GUA1	Ubicom IP3023 CPU
D-Link	DI-784	A1/A2/B1	KA2DI774VB1.	Atheros AR5312A SOC 1MB Flash/16MB RAM
D-Link	DIR-301	A1	KA2WBR1310B1	Atheros AR2317 SOC 2MB Flash/8MB RAM
D-Link	DIR-501	A1	KA2IR501A1	Realtek RTL8196C SOC 2MB Flash/16MB RAM
D-Link	DIR-524	A1	KA2IR524A1	Broadcom BCM5356 SOC 2MB Flash/16MB RAM
D-Link	DIR-600	Cx	KA2DIR600C(1/2)	Ralink RT3350 SOC 2MB Flash/8MB RAM
D-Link	DIR-600	D1	KA2IR600D1	Ralink RT5350 SOC 2MB Flash/8MB RAM
D-Link	DIR-600L	A1	KA2IR600LA1	Realtek RTL8196C SOC 4MB Flash/32MB RAM
D-Link	DIR-600L	B1	KA2IR600LB1	Realtek RTL8196C SOC 4MB Flash/32MB RAM
D-Link	DIR-605L	A1	KA2IR605LA1	Realtek RTL8196C SOC 4MB Flash/32MB RAM
D-Link	DIR-615	A1	KA2DIR615A1	Marvell MV88F5180 SOC 8MB Flash/32MB RAM
D-Link	DIR-615	B2	KA2DIR615B2	Ubicom IP5090U CPU 2MB Flash/16MB RAM
D-Link	DIR-615	F1/F2/F3	KA2DIR615F(1/2/3)	Realtek RTL8196B SOC 2MB Flash/16MB RAM
D-Link	DIR-615	M1		Realtek RTL8196C SOC 4MB Flash/32MB RAM
D-Link	DIR-615	Q1		Realtek RTL8196C SOC 4MB Flash/32MB RAM
D-Link	DIR-615	S1	KA2IR615S1	Realtek RTL8196E SOC 2MB Flash/8MB RAM
D-Link	DIR-615	T1	KA2IR615T1	Realtek RTL8196E SOC 2MB Flash/8MB RAM
D-Link	DIR-625	A1/A2	KA2DIR625A1	Ubicom IP3023 CPU 4MB Flash/16MB RAM
D-Link	DIR-625	C1	KA2DIR625C1	

Known\_incompatible\_devices

				Ubicom IP5100U CPU 4MB Flash/16MB RAM
D-Link	DIR-625	C2	KA2DIR615B2	Ubicom IP5100U CPU 4MB Flash/16MB RAM
D-Link	DIR-628	A1	KA2DIR628A1	Ubicom IP5100U CPU 4MB Flash/16MB RAM
D-Link	DIR-628	A2	KA2DIR628A2	Ubicom IP5100U CPU 4MB Flash/16MB RAM
D-Link	DIR-635	A1	KA2DIR635A1	Ubicom IP3023 CPU 4MB Flash/16MB RAM
D-Link	DIR-635	B1	KA2DIR635B1	Ubicom IP5100U CPU 4MB Flash/16MB RAM
D-Link	DIR-635	B3	KA2DIR635B3	Ubicom IP5100U CPU 4MB Flash/16MB RAM
D-Link	DIR-652	A1	KA2IR652A1	Ubicom IP7150U CPU 8MB Flash/64MB RAM
D-Link	DIR-655	A1/A2	KA2DIR635A1	Ubicom IP5160U CPU 4MB Flash/16MB RAM
D-Link	DIR-655	A3	KA2DIR655A3	Ubicom IP5160U CPU 4MB Flash/16MB RAM
D-Link	DIR-655	A4	KA2DIR655A4	Ubicom IP5160U CPU 4MB Flash/16MB RAM
D-Link	DIR-655	B1	KA2IR655B1	Ubicom IP7150U CPU 8MB Flash/64MB RAM
D-Link	DIR-657	A1	KA2IR657A1	Ubicom IP7160U CPU 16MB Flash/128MB RAM
D-Link	DIR-665	A1	KA2IR665A1	Marvell MV88F6281 SOC 16MB Flash/128MB RAM
D-Link	DIR-803	A1	KA2IR803A1	Realtek RTL8881AQ SOC
D-Link	DIR-818L	A1	KA2IR818LA1	Realtek RTL8881AB SOC 16MB Flash/128MB RAM
D-Link	DIR-820L	A1	KA2IR820LA1	Realtek RTL8197D SOC 8MB Flash/64MB RAM
D-Link	DIR-825	A1	KA2DIR825A1	Ubicom IP5170U CPU 4MB Flash/16MB RAM
D-Link	DIR-850L	A1	KA2IR850LA1	Realtek RTL8197D SOC 128MB Flash/128MB RAM
D-Link	DIR-850L	B1	KA2IR850LB1	Realtek RTL8197D SOC 8MB Flash/128MB RAM
D-Link	DIR-855	A1	KA2DIR855A1	Ubicom IP5170U CPU 4MB Flash/16MB RAM
D-Link	DIR-855	A2	KA2DIR855A2	Ubicom IP5170U CPU 4MB Flash/16MB RAM
D-Link	DWL-7100AP	A1	KA22003040018-1	Atheros AR5312A CPU 2MB Flash/16MB RAM
D-Link	DWL-G730	B1	KA2DWLG730APB1	

Known\_incompatible\_devices

				Marvell MV88W8510 SOC 2MB Flash/8MB RAM
D-Link	WBR-2310	A1	F332177004296	Atheros AR2316A SOC 2MB Flash/8MB RAM
DSE	XH9948			Marvell based 8MB RAM
Edimax	3G-6200nL		NDD9512100913	Ralink RT3050F SOC 2MB Flash/16MB RAM
Edimax	BR-6204Wg		NDD9562040507	Realtek RTL8186 SOC 2MB Flash/16MB RAM
Edimax	BR-6216MG		NDD9562160602	RDC R3210 CPU 4MB Flash/16MB RAM
Edimax	BR-6258N		NDD9562581023	Realtek RTL8196 SOC 4MB Flash/16MB RAM
Edimax	BR-6304Wg		NDD9562040507	Realtek RTL8186 SOC 4MB Flash/16MB RAM
Engenius	ESR1221N		U2M-SR1221N10	Realtek RTL8196 SOC 2MB Flash/16MB RAM
Hawking	HWBA54G	v0	MQ4AP900	Ubicom IP2022 CPU
HP (Procurve wireless AP 420)	J8130A (Wireless AP-420)	420na	HEDWA4101ACCAA	Freescale MPC8241LZQ CPU 4MB Flash/16MB RAM
Level One	WBR-6001	-	-	Amrisc 20010 CPU 2MB Flash/8MB RAM
Level One	WGR-6012	v1	PBLCDE570AM	Ralink RT3052 SOC 2MB Flash/16MB RAM
Linksys	BEFSR41	v4.3	-	Realtek RTL8650B SOC 1MB Flash/8MB RAM
Linksys	BEFW11S4	v4	PKW-BEFW11S4V4	Marvell MV88W8500 SOC 1MB Flash/4MB RAM
Linksys	E4200	v2	Q87-E4200v2	Marvell MV88F6282 SOC 128MB Flash/128MB RAM
Linksys	EA3500	v1	Q87-EA3500	Marvell MV88F6282 SOC 64MB Flash/64MB RAM
Linksys	EA4500	v1	Q87-EA4500	Marvell MV88F6282 SOC 128MB Flash/128MB RAM
Linksys	WAG200G	v1	Q87-WAG200G	TI CPU
Linksys	WET11	v1/v2	PKW-WETAP11	Ubicom IP2022 CPU
Linksys	WRE54G	v2	Q87-WRE54GV2	Marvell MV88W8515 SOC 1MB Flash/8MB RAM
Linksys	WRE54G	v3	Q87-WRE54GV3	Marvell MV88W8515 SOC 1MB Flash/8MB RAM
Linksys	<u>WRT100</u>	v1	Q87-WRT100	Ralink RT2780F CPU 4MB Flash/16MB RAM
Linksys	<u>WRT110</u>	v1	Q87-WRT110	Ralink RT2780F CPU 4MB Flash/16MB RAM

Known\_incompatible\_devices

Linksys	WRT120N	v1	Q87-WRT120N	Atheros AR7240 CPU 2MB Flash/32MB RAM
Linksys	WRT330N	v1	Q87-WRT330N	Ubicom IP5160U CPU 4MB Flash/32MB RAM
Linksys	WRT350N	v2.x	Q87-WRT350NV2	Marvell MV88F5181 SOC 8MB Flash/32MB RAM
Linksys	WRT54GX2	v1	Q87-WRT54GX2	Realtek RTL8651B SOC Airgo wlan
Linksys	WRT54G2	v1.5	Q87-WRT54G2V15	Atheros AR2317 SOC 2MB Flash/16MB RAM
Linksys	WRT54GC	v2	Q87-WRT54GCV2	Marvell MV88W8510 SOC 1MB flash/8MB RAM
Linksys	WRT54GH	-	Q87-WRT54GH	Ralink RT3050 SOC 2MB Flash/8MB RAM
Linksys	WRT54GP2		Q87-WRT54GP2	Marvell MV88W8510 SOC 2MB Flash/8MB RAM
Netgear	DG834G	v1 v2 v3	PY3DG834G PY3DG834GV2 PY305300023	ADSL Modem
Netgear	DGN1000	-	PY309300114	ADSL Modem
Netgear	D6300	-	-	ADSL Modem
Netgear	DGN3700	v1 v2	PY310100129 PY311400180	ADSL Modem
Netgear	JWNR2000	v1	PY309100106	Realtek RTL8196B SOC 4MB Flash/32MB RAM
Netgear	JWNR2000	v2	PY310400149	Realtek RTL8196C SOC 4MB Flash/32MB RAM
Netgear	MR814	v2	PY3MR814V2	Marvell MV88W8500 SOC 1MB Flash/4MB RAM
Netgear	WGR614	v2	PY3WGR614v2	Atheros AR2312A CPU 2MB Flash/8MB RAM
Netgear	WGR614	v3	PY3WGR614v3	Atheros AR2312A CPU 2MB Flash/8MB RAM
Netgear	WGR614	v4	PY3WGR614v4	Marvell MV88W8510 SOC 1MB Flash/2MB RAM
Netgear	WGR614	v5	PY3WGR614v5	Broadcom BCM5350 SOC 1MB Flash/8MB RAM
Netgear	WGR614	v6	PY305100002	1MB Flash! ( <u>Note: some v6 may have 2MB</u> )
Netgear	WGR614	v7	PY306100036	Atheros AR2317 SOC 2MB Flash/8MB RAM
Netgear	WGR614	v9	PY306400057	Broadcom BCM5354 SOC 2MB Flash/8MB RAM incompatible nvram size
Netgear	WGR614	v10	PY306400117	Broadcom BCM5356 SOC 4MB Flash/16MB RAM

Known\_incompatible\_devices

				incompatible nvram size
Netgear	WGT624	v3	PY3WGT624V3	Atheros AR2316 SOC 2MB Flash/8MB RAM
Netgear	WNR1000	v3	PY306400117	Broadcom BCM5356 SOC 4MB Flash/16MB RAM incompatible nvram size
Netgear	WNR1500	v1	PY312200196	Realtek RTL8196 SOC 4MB Flash/32MB RAM
Netgear	WNR2000	v1	PY308200083	Atheros AR9132 CPU 4MB Flash/32MB RAM U-Boot must be replaced
Netgear	WNR2000	v4	PY312300212	Atheros AR9341 SOC 4MB Flash/32MB RAM U-Boot must be replaced
Netgear	WNR2000	v5	PY314100256	Qualcomm QCA9531 SOC 4MB Flash/32MB RAM U-Boot must be replaced
Netgear	WNR3500	v1	PY307300074	Marvell MV88F5180 SOC 8MB Flash/32MB RAM
Netgear	WNR834M	-	PY306100038	Marvell MV88F5180 SOC
Netgear	WNR854T	-	PY306200049	Marvell MV88F5180 SOC 8MB Flash/32MB RAM
Netgear	WPN824	v1	PY3WPON824	Atheros AR2313 CPU 2MB Flash/16MB RAM
Netgear	WPN824	v2	PY305300021	Atheros AR2316A SOC 2MB Flash/16MB RAM
Netgear	WPN854T		PY306200049	Marvell MV88F5180 SOC 8MB Flash/32MB RAM
Netis	WF2411		T58WF2411R	Realtek RTL8196C SOC 4MB Flash/16MB RAM
SMC	SMC2404WBR	V1.0	O7J-GL242204P (WLAN card)	Samsung S3C4510B CPU 1MB FLASH/8MB RAM
SMC	SMCWBR14T-G EU		RAXWG4005E1	Atheros 2316A SOC 2MB Flash/16MB RAM
Senao/Engenius	EOC-8610S EXT	v1.1	U2M-OC86107001	Ubicom IP3023 CPU 4MB Flash/16MB RAM
Senao/Engenius	ESR-9710	-	U2M-SR97108001	Ubicom IP5160U CPU 4MB Flash/16MB RAM
Senao/Engenius	ESR-9855G	-	U2M-SR9855G	Ubicom IP7150U CPU 8MB Flash/64MB RAM
Sparklan	WX-6615GS	-	RYK-WX6615GS	Atheros AR2316A SOC 2MB Flash/8MB RAM
Tenda	W268R		V7TW268R	Ralink RT3050 SOC 2MB Flash/16MB RAM
Tenda	W308R		V7TW308R	Broadcom BCM5357 SOC 2MB Flash/16MB RAM



Known\_incompatible\_devices

Tenda	W311R+			Broadcom BCM5356 SOC 2MB Flash/8MB RAM
TP-Link	TD-W8960N	v3	TE7TDW8960NV3	Modem/Router combo
TP-Link	TL-WA5110G	v1	TE7WA5110G	Atheros AR2315 SOC 2MB Flash/8MB RAM
TP-Link	TL-WDR7500 (aka Archer C7v1)		-	Qualcomm QCA9558 SOC incompatible 5GHz card
TP-Link	TL-WR340G	v1	TE7WR340G	Atheros AR2317 SOC 2MB Flash/8MB RAM
TP-Link	TL-WR542G	v6.5	TE7WR54XGV2	Atheros AR2317 SOC 2MB Flash/8MB RAM
TP-Link	TL-WR641G	v4		Atheros AR2318 SOC 2MB Flash/16MB RAM
TP-Link	TL-WR700N	v1	TE7WR700N	Atheros AR9331 SOC 2MB Flash/16MB RAM
TP-Link	TL-WR702N	v1	TE7WR702N	Atheros AR9331 SOC 2MB Flash/16MB RAM
TP-Link	TL-WR706N	v1	Chinese version only!	Atheros AR9331 SOC 2MB Flash/16MB RAM
TP-Link	TL-WR720N	v1	TE7WR720N	Atheros AR9331 SOC 2MB Flash/8MB RAM
TP-Link	TL-WR720N	v2	TE7WR720Nv2	Atheros AR9331 SOC 2MB Flash/8MB RAM
TP-Link	TL-WR840N	v2	Chinese version only!	Atheros AR9331 SOC 2MB Flash/16MB RAM
TP-Link	TL-WR841N(D)	v8	Chinese version only!	Atheros AR9341 SOC 4MB Flash/16MB RAM BSP+VXWorks
TP-Link	TL-WR841N(D)	v9	Chinese version	Atheros AR9341 SOC 2MB Flash/16MB RAM
TP-Link	TL-WR1042ND	v1	TE7WR1042ND	Realtek RTL8198 CPU 8MB Flash/64MB RAM
Trendnet	TEW-431BRP/A	1.02	-	Marvell MV88W8510 SOC 1MB Flash/4MB RAM
Trendnet	TEW-432BRP	C1.1R	S9ZTEW432BRP	Atheros AR2317 SOC 2MB Flash/8MB RAM
Trendnet	TEW-432BRP	D1.1R	S9ZTEW432BRPD	Realtek RTL8186 SOC 2MB Flash/8MB RAM
Trendnet	TEW-652BRP	v2.xR	S9ZTEW652BRP2	Realtek RTL8196 SOC 4MB Flash/32MB RAM
Trendnet	TEW-652BRP	v3.xR	XU8TEW652BRPV3	Realtek RTL8196 SOC 4MB Flash/32MB RAM
Trendnet	TEW-731BR	v1.xR	XU8TEW652BRPV3	Realtek RTL8196 SOC 4MB Flash/32MB RAM
UNICOM	802.11g wireless router	BOARD # MO1-914M-A10	MQ4ARM914	Marvell MV88W8510 SOC 1MB Flash/4MB RAM

Known\_incompatible\_devices

<b>Brand</b>	<b>Model Number</b>	<b>Hardware revision</b>	<b>FCC-ID</b>	<b>Additional notes</b>
--------------	-------------------------	------------------------------	---------------	-------------------------