

Contents

- 1 Read Me First!
 - ◆ 1.1 About this list
 - ◆ 1.2 Broadcom and ADM FAQ
 - ◇ 1.2.1 Which version may I flash?
 - ◇ 1.2.2 2MB flash
 - ◇ 1.2.3 4MB flash
 - ◇ 1.2.4 8MB flash or more
 - ◆ 1.3 Atheros, Ralink and any other FAQ
 - ◇ 1.3.1 2MB flash
 - ◇ 1.3.2 4MB flash
 - ◇ 1.3.3 8MB flash or more
- 2 HOWTO/FAQ to the Comparison Table
- 3 Supported Devices
 - ◆ 3.1 3com
 - ◆ 3.2 Abocom
 - ◆ 3.3 Accton
 - ◆ 3.4 Aceex
 - ◆ 3.5 Actiontec
 - ◆ 3.6 ADI Engineering
 - ◆ 3.7 Airlink 101
 - ◆ 3.8 Airlive / Ovislink
 - ◆ 3.9 Alfa Networks
 - ◆ 3.10 Allnet
 - ◆ 3.11 Anaptyx Wireless Dynamics
 - ◆ 3.12 Arada Systems
 - ◆ 3.13 Askey
 - ◆ 3.14 Asus
 - ◆ 3.15 Belkin
 - ◆ 3.16 Bountiful
 - ◆ 3.17 Browan
 - ◆ 3.18 Buffalo
 - ◆ 3.19 Conceptronic
 - ◆ 3.20 Cisco
 - ◆ 3.21 Compex
 - ◆ 3.22 Conrad Elektronik
 - ◆ 3.23 Corega
 - ◆ 3.24 Dell
 - ◆ 3.25 Devolo
 - ◆ 3.26 Digitus
 - ◆ 3.27 D-Link
 - ◆ 3.28 Doodle Labs
 - ◆ 3.29 Dynex
 - ◆ 3.30 Edimax
 - ◆ 3.31 Encore
 - ◆ 3.32 EnGenius
 - ◆ 3.33 Exel Networks

Supported_Devices

- ◆ [3.34 Fluidmesh](#)
- ◆ [3.35 FON](#)
- ◆ [3.36 Fry's Electronics](#)
- ◆ [3.37 Gateway](#)
- ◆ [3.38 Gateworks](#)
- ◆ [3.39 Guest Internet Solutions](#)
- ◆ [3.40 Hame](#)
- ◆ [3.41 Intellinet \(Reichelt\)](#)
- ◆ [3.42 Iomega](#)
- ◆ [3.43 JJPlus](#)
- ◆ [3.44 Lanready](#)
- ◆ [3.45 Linksys \(a devision of Belkin - formerly Cisco\)](#)
 - ◇ [3.45.1 Linksys \(Wired\)](#)
 - ◇ [3.45.2 Linksys \(Wireless a/b/g/n\)](#)
 - ◇ [3.45.3 Linksys \(Wireless a/b/g\)](#)
 - ◇ [3.45.4 Linksys Valet](#)
- ◆ [3.46 Logilink](#)
- ◆ [3.47 MagicBox](#)
- ◆ [3.48 Meraki](#)
- ◆ [3.49 Microsoft](#)
- ◆ [3.50 Mikrotik Routerboard](#)
- ◆ [3.51 Mitsubishi](#)
- ◆ [3.52 Motorola](#)
- ◆ [3.53 MSI](#)
- ◆ [3.54 MTN Electronics](#)
- ◆ [3.55 NewMedia](#)
- ◆ [3.56 NetComm](#)
- ◆ [3.57 NETCORE](#)
- ◆ [3.58 Netgear](#)
- ◆ [3.59 Nokia](#)
- ◆ [3.60 OpenMesh](#)
- ◆ [3.61 OpenRB](#)
- ◆ [3.62 OSBRiDGE](#)
- ◆ [3.63 Ovislink](#)
- ◆ [3.64 PC-Engines](#)
- ◆ [3.65 Planex aka PCi](#)
- ◆ [3.66 Ravo](#)
- ◆ [3.67 RayTalk](#)
- ◆ [3.68 Repotec](#)
- ◆ [3.69 RFNet Technologies](#)
- ◆ [3.70 Rosewill](#)
- ◆ [3.71 Ruckus](#)
- ◆ [3.72 Senao / EnGenius](#)
- ◆ [3.73 Siemens](#)
- ◆ [3.74 Sitecom](#)
- ◆ [3.75 Snapgear](#)
- ◆ [3.76 SOEKRIS Engineering](#)

Supported_Devices

- ◆ [3.77 SparkLAN](#)
- ◆ [3.78 Straight Core](#)
- ◆ [3.79 Technaxx](#)
- ◆ [3.80 Techniclan](#)
- ◆ [3.81 Tonze](#)
- ◆ [3.82 Toshiba](#)
- ◆ [3.83 TP-Link](#)
- ◆ [3.84 Tranzeo](#)
- ◆ [3.85 TRENDnet](#)
- ◆ [3.86 T&W](#)
- ◆ [3.87 Ubiquiti](#)
- ◆ [3.88 US Robotics](#)
- ◆ [3.89 Valemount](#)
- ◆ [3.90 Verizon](#)
- ◆ [3.91 Viewsonic](#)
- ◆ [3.92 VSCOM](#)
- ◆ [3.93 Watchguard](#)
- ◆ [3.94 WiliGear](#)
- ◆ [3.95 WinStars](#)
- ◆ [3.96 Wistron](#)
- ◆ [3.97 ZCOM](#)
- [4 Note on DUAL and MULTI Wan routers](#)
- [5 List of Incompatible Routers](#)

Read Me First!

About this list

This page lists and compares all devices that are known to work with DD-WRT, some of them are not yet supported but are a work-in-progress (WIP).

If you don't find your hardware below, then it is probably not yet supported and you risk breaking it. See **Known incompatible devices** for the black list, or refer to Router detection to determine whether or not support can be added in the future.

If you are looking for a router to buy see **Firmware FAQ#Which router should I buy?**

Broadcom and ADM FAQ

Which version may I flash?

See Which v24 build do I flash onto my Broadcom router?.

Supported_Devices

2MB flash

The micro version of DD-WRT is the only version for routers with 2MB flash. This is a stripped-down firmware with only the basic features to fit in the limited space. Users should not expect to be able to install additional software packages on such devices. Because of the limited features of the micro version, **users are strongly recommended to avoid buying devices with only 2MB of flash memory.**

The 2MB flash support is for Broadcom based routers only, all other platforms requires at least 4MB flash!

Despite the limitations of micro version compared to the full version, if you already own a device with 2MB of flash memory, installing the micro DD-WRT version is likely to add additional functionality that your device's original firmware did not support.

4MB flash

With 4MB of flash you can run the standard build (Linux kernel 2.4) or the small build (Linux kernel 2.6). These builds are usually enough for the majority of users but anyone who intend to load additional software packages on their router should get a router with 8MB or more of flash memory.

Do not flash the Mega build on devices with 4MB flash memory. Mega requires 8 or more MB flash.

8MB flash or more

You can flash the Mega, Big, or standard++ builds that are bigger than 4MB. Check the tables below for support.

Atheros, Ralink and any other FAQ

These devices have special builds only for using on the respective unit. There exists NO other builds than those in the specific folder for the unit.

2MB flash

Not supported by dd-wrt, Atheros and Ralink builds needs at least 4MB of flash.

4MB flash

Atheros and Ralink builds are not prefixed with mini, small, std, or mega. 4MB is usually enough for basic dd-wrt functions but there are a few routers where certain functions had to be removed due to space limitations.

8MB flash or more

This is the flash size needed for those users who intend to load additional software packages on their router or want to run a build compiled with additional functionality.

HOWTO/FAQ to the Comparison Table

- Please keep it simple to administer for all users! **One line, one device! NO** rowspanning stuff!
 - WIP = Work In Progress (Located under version). Sometimes we need the hardware to do the port. So feel free to contact [Sash](#) via e-mail and provide us with the hardware so we can get this started!
 - NO static linking to DD-WRT firmware releases, they get old very fast!!
 - NO static linking to manufacturers product page, they only work until the mfgr reorganizes his web site!
 - This table is a work-in-progress and likely contains errors and omissions, please update it as needed and fill in the blanks if you can.
- **WIP** = Work In Progress (it is being worked on)
 - **TBD** = To Be Done (will be done some time in the future)

Supported Devices

3com

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
3CRWER100-75	?	O9C-WL537	Atheros AR2315@180	16	4	Atheros	b/g	-	1	1	4 LAN 1 WAN

Abocom

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
WAP2102	?	MQ4WAP2102	Atheros AR2317@180	16	4	Atheros	b/g	-	?	-	1 LAN or WAN

Supported_Devices

Accton

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
<u>MR3201A</u>	?	HED-MR3201A	Atheros AR2315@180	16	8	Atheros	b/g	-	1	Y	1 WAN or LAN
<u>MR3202a</u>	-	HEDMR3202A	Atheros AR2317@180	16	8	Atheros	b/g	-	?	?	1 WAN 1 LAN

Aceex

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Inp [V/]
NR22/Y	-	IFA-NRXX	Ralink RT3052F@380	32	4	Ralink	b/g/n	-	1	-	4 LAN 1 WAN	9V/1

Actiontec

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
<u>MI424WR</u>	A	LNQ802MRG	Xscale IXP425@533	32	8	depends on card	ralink b/g (must be replaced)	1	1	1	4 LAN 1 WAN
<u>MI424WR</u>	C	LNQ802MAG	Xscale IXP425@533	32	8	depends on card	Atheros b/g	1	1	1	4 LAN 1 WAN
<u>MI424WR</u>	D	LNQ802MAG		32	8		b/g	1	1	-	-

Supported_Devices

			Xscale IXP425@533			depends on card						4 LAN 1 WAN
--	--	--	----------------------	--	--	--------------------	--	--	--	--	--	----------------------

ADI Engineering

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	Po In [V]
Coyote	-	?	Xscale IXP425@533	64- 128	16- 32	-	depends on card	2	1	1	4 LAN 1 WAN	?	?
<u>Pronghorn SBC 210</u>	-	?	Xscale IXP420@266	32	8	-	depends on card	2	1	?	1 LAN	802.3af	5, 30
<u>Pronghorn Metro SBC</u>	-	?	Xscale IXP425@533	64	16	-	depends on card	4	1	?	1 LAN, 1 WAN	yes	17- & 60

Airlink 101

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. por cour
<u>AR335W</u>	?	RRK-AR335W	Atheros AR2317@182	16	4	Atheros	b/g	-	?	1	4 LA 1 WAN
<u>AR430W</u>	V1	RRK-AR430W	Atheros AR2318@182	16	4	Atheros	b/g	-	1	1	4 LA 1

Supported_Devices

												WAN
AP431W	?	RRK-AP431W	Atheros AR2313A@180	16	4	Atheros	b/g	-	1	1		1LAN
<u>AR670W</u>	?	RRK-WRGN16	Ralink RT2880F@266	32	4	Ralink RT2820L	b/g/n	has pads	1	1		4 LAN 1 WAN
<u>AR690W</u>	?	RRK-WRGN20	Ralink RT2880F@266	32	4	Ralink RT2820L	b/g/n	-	1	?		4 LAN 1 WAN

Airlive / Ovislink

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth port count
Airmax 5	?	?	Atheros AR2312@180?	32	8	Atheros AR5112A SoC?	a/b/g/n @ 20dBm?	?	1?	?	2 LAN 1 WAN
IGR-2500	?	?	IXP425 @ 533	128	4	-	-	?	1	?	2 LAN 5 WAN
RS-1200	?	?	IXP425 @ 266	32	8	-	-	?	1	?	2 LAN 2 WAN
<u>WHA-5500CPE</u>	?	?	Atheros AR2312@180	32	4	Atheros AR5112A SoC	a/b/g/h @ 20dBm	?	1	?	2 LA 1 WAN
<u>WHA-5500CPE-NT</u>	?	?	Atheros AR2312@180	32	4	Atheros AR5112A SoC	a/b/g/h @ 20dBm	?	1	?	1 LA WAN
<u>WLA-5000</u>	?	?	Atheros AR2312@180	32	4	Atheros AR5112A	a/b/g/h @ 20dBm	?	1	?	1 LA WAN

Supported_Devices

						SoC					
<u>WLA-9000ap</u>	?	?	Atheros AR5312@220	32	8	Atheros	a/b/g @ 23dBm	?	1	?	2 LAN 1 WAN

Alfa Networks

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port
Solo48 (AP48)	?	?	Atheros AR2313@180	32	8	Atheros	a/b/g/h @ 30dBm	?	1	?
AIP-W411		UQ2W411	Atheros AR7240@400	32	4	Atheros AR9285@17dBm	b/g/n 1x1:1	-	1	?
AIP-W502U	?	?	Atheros AR9130@400	32	8	Atheros AR9102	b/g/n 2x2:2	-	Yes	Yes

Allnet

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
ALL0258	-	-	Atheros AR2313@180	32	8	1	AR5112 a/b/g @ 28dbm	-	1	?	1 LAN
All0277	-		Broadcom BCM4702@125	16	4	Broadcom	b/g	1	-	yes	4 LAN 1 WAN

Supported_Devices

AI10285	?	?	Atheros 2312a@180	16	4	Atheros	b/g	-	1	1	1	LAN	-
ALL02762	-	-	Broadcom BCM5354@240	16	4	1	b/g	-	-	1	4	LAN 1 WAN	
<u>ALL391AP</u>	-	?	Xscale IXP420@266	32	8	Atheros	1x a/b/g/n	4	1	Yes	1	LAN 1 WAN	ye
<u>ALL392BR</u>	-	?	Xscale IXP420@266	32	8	Atheros	2x a/n @ 30dBm	4	1	Yes	1	LAN 1 WAN	ye
<u>ALL392MAP</u>	-	?	Xscale IXP420@266	32	8	Atheros	1x a/n @ 30dBm, 1x a/b/g/n	4	1	Yes	1	LAN 1 WAN	ye
<u>ALL392MRAP</u>	-	?	Xscale IXP420@400	32	8	Atheros	2x a/n @ 30dBm	4	1	Yes	1	LAN 1 WAN	ye

Anaptyx Wireless Dynamics

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	Power Input [V/A]
-------	-------------	-----------	----------------------------------	-------------	---------------	-----------------	------------------------------	-------------	----------------	--------------	-----------------------	-----	-------------------------

Supported_Devices

ID-2	-	Atheros AR710@680	64	16	-	2x a/b/g/h	3	1	yes	3 LAN WAN	yes	5- 24
OD-2	-	Atheros AR710@680	64	16	-	2x a/b/g/h	3	1	yes	3 LAN WAN	yes	5- 24
OMW	-	Atheros AR710@680	64	16	-	depends on card	3	1	yes	3 LAN WAN	yes	5- 24
AWR-100	-	Atheros AR710@680	64	16	-	depends on card	3	1	yes	3 LAN WAN	yes	5- 24

Arada Systems

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	Port In [V]
MaxR-7100	-	?	Atheros AR7130@300	32	8	-	depends on card	1	1	1	2 LAN WAN	yes	12 & 18
MaxR-7200	-	?	Atheros AR7161@680	64	8	-	depends on card	2	1	1	4 LAN 1 WAN	yes	8- & 48
MaxR-7300	-	?	Atheros AR7161@680	64	8	-	depends on card	3	1	1	4 LAN 1 WAN	yes	8- & 48

Askey

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port
RT210W	-	H8N-RT210W	Broadcom BCM4710@125	16	4	Broadcom	b/g	1	-	?

Supported_Devices

RT480W	-	H8NRT480W	Broadcom BCM4712@200	8	4	Broadcom	b/g	-	?	?
RT2100W	RT2100W-D65	-	Broadcom BCM4710@125	?	?	Broadcom	b/g	?	?	?
RT220XD	-	?	Broadcom BCM4704@264	16	4	Broadcom	b/g	?	-	?
RT2206D?	RT2206D-D56	-	Broadcom BCM4704@264	16	4	Broadcom	b/g	?	?	?

Asus

WARNING: It is recommended to use ASUS Firmware restoration tool for ASUS routers initial flash (use *.TRX file)

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	S
<u>RT-AC56U</u>	-	MSQ-RTAC56U	Broadcom BCM4708A0@800	256	128	Broadcom BCM4352 + BCM43217	a/c 900 b/g/n 300	-	1
<u>RT-AC66U</u>	-	MSQ-RTAC66U	Broadcom BCM4706@600	256	128	Broadcom BCM43460 + BCM4331	a/c 1300 b/g/n 450	-	1
RT-AC68P	-	MSQ-RTAC68Uv2	Broadcom BCM4709@1000	256	128	Broadcom BCM4360 x2	a/c 1300 b/g/n 600	-	1
<u>RT-AC68U</u>	-	MSQ-RTAC68U	Broadcom BCM4708A0@800	256	128	Broadcom BCM4360 x2	a/c 1300 b/g/n 600	-	1
RT-AC87U	-	MSQ-RTAC87U	Broadcom BCM4708@800	128	128	Broadcom + Quantenna QSR1000	a/c 1700 b/g/n 600	-	-
<u>RT-G32</u>	A	MSQRTG32		16	4	Atheros	b/g	-	?

Supported_Devices

			Atheros AR2317@180						
<u>RT-G32</u>	B1	MSQ-RTG32	Ralink RT3052@380	16	4	Ralink	b/g/n	-	1
<u>RT-N10</u>	-	MSQ-RTN10	Broadcom BCM5356@300	16	4	Broadcom	b/g/n	-	Y
<u>RT-N10+</u>	B1	MSQRTN10B	RT3050F@384	32	4	Ralink	b/g/n	-	1
<u>RT-N10P</u>	-	MSQ-RTN10P	Broadcom BCM5356C0@300	32	8	Broadcom	b/g/n 1T1R	-	Y
<u>RT-N10+</u>	D1	MSQ-RTN10PLUS	Broadcom BCM5356@300	16	4	Broadcom	b/g/n	-	Y
<u>RT-N10U</u>	-	MSQ-RTN10U	Broadcom BCM5357@300	32	8	Broadcom	b/g/n	-	Y
<u>RT-N10U BLACK</u>	-	MSQ-RTN10UB	Broadcom BCM5357@300	32	8	Broadcom	b/g/n	-	Y
<u>RT-N12</u>	-	MSQ-RTN12	Broadcom BCM4716@300	32	4	Broadcom	b/g/n	-	Y
<u>RT-N12</u>	B1	MSQ-RTN12B	Broadcom BCM5357@300	32	8	Broadcom	b/g/n	-	Y
RT-N12	C1	MSQ-RTN12C	Broadcom BCM5357@300	32	4	Broadcom	b/g/n	-	Y
<u>RT-N12</u>	D1	MSQ-RTN12D	Broadcom BCM5357C0@300	32	8	Broadcom	b/g/n	-	Y

Supported_Devices

<u>RT-N13</u>	-	MSQ-RTN13	Ralink RT2880@266	32	4	Ralink	b/g/n	-	y
<u>RT-N13U</u>	-	MSQ-RTN13U	Ralink RT3052@380	32	4	Ralink	b/g/n	-	y
<u>RT-N13U</u>	B	MSQ-RTN13U	Ralink RT3052@380	64	8	Ralink	b/g/n	-	y
<u>RT-N14U</u>	C1	MSQ-RTN14U	Mediatek MT7620N@600	64	16	SOC	b/g/n 2T2R	-	y
<u>RT-N15</u>	-	MSQ-RTN15	Ralink RT2880@266	32	4	Ralink	b/g/n	-	Y
<u>RT-N15U</u>	-	MSQ-RTN15U	Broadcom BCM5357r2@500	64	8	SOC	b/g/n 2T2R	-	Y
<u>RT-N16</u>	-	MSQRTN16	Broadcom BCM4718@480	128	32	Broadcom	b/g/n	-	Y
<u>RT-N18U</u>	-	MSQ-RTN18U	Broadcom BCM47081@800	256	128	SOC	b/g/n 3T3R	-	Y
<u>RT-N53</u>	-	MSQ-RTN53	Broadcom BCM5358U@300	32	8	SOC + Broadcom BCM43236	a/b/g/n	-	Y
<u>RT-N66U</u>	-	MSQ-RTN66U	Broadcom BCM4706@600	256	32	Broadcom BCM4331 x 2	a/b/g/n	-	Y
<u>WL-300g</u>	-	MSQWL300G	Broadcom BCM4710@125	16	4	Broadcom	b/g	-	-
<u>WL-330gE</u>	-	MSQWL330GE	Broadcom BCM5354r2@240	16	4	Broadcom	b/g	1	-
<u>WL-330N3G</u>	-	MSQ-WL330N3G		32	4	Ralink SOC	b/g/n	-	-

Supported_Devices

			Ralink RT3050F@320						
<u>WL-500b</u>	-	MSQWL500B	Broadcom BCM4710@125	16	4	Broadcom	b (maybe wlan must be replaced to work)	1	-
<u>WL-500g</u>	-	MSQWL500G	Broadcom BCM4710@125	16	4	Broadcom	b/g	1	-
<u>WL-500g Deluxe</u>	-	MSQWL500GD	Broadcom BCM5365@200	32	4	Broadcom	b/g	-	1
<u>WL-500gP</u>	-	MSQWL500GP	Broadcom BCM4704@264	32	8	Broadcom	b/g	1	1
<u>WL-500gP V2</u>	v2	MSQWL500GP V2	Broadcom BCM5354@240	32	8	Broadcom BCM4318	b/g	-	1
<u>WL-500W</u>	-	MSQWL500W	Broadcom BCM4704@264	32	8	Broadcom	b/g/n	1	1
<u>WL-520g</u>	-	MSQWL520G	Broadcom BCM5350@200	8	2	Broadcom	b/g	?	Y
<u>WL-520gC</u>	-	MSQWL520GUGC	Broadcom BCM5354@240	16	2	Broadcom	b/g	?	-
<u>WL-520gU</u>	-	MSQWL520GUGC	Broadcom BCM5354@240	16	4	Broadcom	b/g	No	Y
<u>WL-550gE</u>	-	MSQWL550GE	Broadcom BCM5352@200	16	4	Broadcom	b/g	?	-
<u>WL-700gE</u>	?	?	Broadcom BCM4780@266	64	2	Broadcom	b/g	?	?

Supported_Devices

--	--	--	--

Belkin

WARNING: Always use TFTP to flash Belkin routers if at all possible! Upgrading dd-wrt from the web interface can lead to a bricked (nonfunctional) unit!

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTA port
F5D7130	-	K7SF5D7130	Broadcom BCM4710@125	8	2	Broadcom mini PCI	b/g	1	-	1
F5D7130	v2xxx	K7SF5D7130A	Broadcom BCM4710@125	8	2	Broadcom mini PCI	b/g	1	-	1
F5D7130uk	v3xxx	-	Broadcom BCM4712@200	8	2	Broadcom	b/g	-	-	1
F5D7130-4	1010 1112	QDS-BRCM1005	Broadcom BCM4710@125	8	2	Broadcom mini PCI	b/g	1	-	1
F5D7230-4	1000 1010 1111 1112 1222de 1223df 1223ef 1232a	H8N-RT210W (1000), QDS-BRCM1005 (1112 1223ef 1232a)	Broadcom BCM4710@125	16	4	Broadcom mini PCI	b/g	1	1	1
F5D7230-4	1000fr 1444	K7SF5D7230-4	Broadcom BCM4712@200	8	2	Broadcom	b/g	yes	1	1

Supported_Devices

F5D7230-4	2000 2000de	K7SF5D7234A (v2000)	Broadcom BCM4712@200	8	2	Broadcom	b/g	-	1	1
F5D7230-4	3000	PD5F5D72304	Broadcom BCM5350@200	8	2	Broadcom	b/g	-	2	1
F5D7231-4	v10xx	K7SF5D72304	Broadcom BCM4712@200	8	2	Broadcom	b/g	-	?	-
F5D7231-4	v11xx	K7SF5D7234A	Broadcom BCM4712@200	8	2	Broadcom	b/g	-	1	1
F5D7231-4	v12xx	H8NRT2406W	Broadcom BCM5352@200	8	2	Broadcom	b/g	-	?	?
F5D7231-4	v2xxx	K7SF5D7231B	Broadcom BCM5352@200	8	2	Broadcom	b/g	-	1	1
F5D7231-4P	v1xxx	K7SF5D7231P	Broadcom BCM4712@200	16	4	Broadcom	b/g	-	-	-
F5D7330	v1xxx, v20xx	K7SF5D7130A	Broadcom BCM4710@125	8	2	Broadcom mini PCI	b/g	1	-	1
F5D8230-4	1001ea	SA3- AGN 0901 AP0100	Broadcom BCM4704@264	16	4	Airgo (must replace mini-pci card with broadcom or other compatible card)	b/g	1	1	1
F5D8232-4	1000 1021uk	K7SF5D8232-4	Atheros AR7141@300	16	8	Atheros	b/g/n	-	1	1
F5D8235-4	v20xx	K7SF5D8235-4B	Ralink RT3052F@380	32	8	SOC	b/g/n	-	1	-
F5D8235-4	v21xx	K7SF5D8235-4B	Ralink RT3052F@380	32	8	SOC	b/g/n	-	1	-

Supported_Devices

F5D8235-4	v3	K7SF5D8235v3	Broadcom BCM4718@480	32	8	SOC	b/g/n	-	1	1
F7D3301 & F7D7301	v1 "Share Max"	K7SF7D3301V1	Broadcom BCM4718@480	64	8	SOC	b/g/n	-	1	1
F7D3302 & F7D7302	v1 "Share"	K7SF7D3302V1	Broadcom BCM4718@480	64	8	SOC	b/g/n	-	1	1
F7D4301 & F7D8301	v1 "Play Max"	K7SF7D4301V1	Broadcom BCM4718@480	64	8	BCM 43224	a/b/g/n	-	1	1
F7D4302 & F7D8302 & F7D9302	v1 "Play"	K7SF7D4302V1	Broadcom BCM4718@480	64	8	BCM 43224	a/b/g/n	-	1	1

Bountiful

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	I P c
<u>BWRG500</u>	-	TDK-BWRG500	Atheros AR2316A@180	16	4	Atheros @ 26dBm	b/g	-	1	yes	4 L 1 W
<u>BWRG1000</u>	-	TDK-BWR54G1	Atheros AR2316A@180	16	4	Atheros @ 29dBm	b/g	-	1	yes	4 L 1 W

Browan

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
BW1251	-	MXF-A950806AG	Xscale IXP425@533	64	16	2	Atheros AR5213A @ a/b/g	2	1	1	1 LAN WAN

Supported_Devices

Buffalo

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port
WAPM- HP- AM 54G54	-	?	Broadcom BCM4704@264	64	8	Broadcom	a/b/g/h	-	1
WBMR-HP-G300N	-	?	Lantiq AR9@333	64	32	Atheros AR9280	b/g/n 2x2:2	1	1
WBR-B11	-	?	Broadcom BCM4710@125	16	4	Broadcom	b/g	1	1
WBR-G54	-	?	Broadcom BCM4710@125	16	4	Broadcom	b/g	1	1
WBR2-G54	-	FDI-04600142-0	Broadcom BCM4712@200	16	4	Broadcom	b/g	-	-
WBR2-G54S	-	FDI-04600142-0	Broadcom BCM4712@200	16	4	Broadcom	b/g	-	-
WCR-GN	-	FDI-09101676-0	Ralink RT3350F@320	16	4	SOC	b/g/n	-	1
WHR-300HP2	v1	FDI000000010	MediaTek MT7620A@580	64	8	SOC	b/g/n 2x2:2	-	1
WHR-300HP2D	v1	FDI000000010	MediaTek MT7620A@580	64	8	SOC	b/g/n 2x2:2	-	1
WHR-600D	v1	FDI000000011	MediaTek MT7620A@580	64	8	SOC + RT5592	b/g/n 2x2:2 a/n 2x2:2	-	1
WHR-1166D	v1	FDI000000020	MediaTek MT7620A@580	128	8	SOC + MT7612E	b/g/n 2x2:2 an/ac 2x2:2	-	1
<u>WHR-G54S</u>	-	FDI-04600264-0	Broadcom BCM5352@200	16	4	Broadcom	b/g	-	1
<u>WHR-G125</u>	-	FDI-09101584-0		16	4	Broadcom	b/g	-	1

Supported_Devices

			Broadcom BCM5354@240						
<u>WHR-G300N</u>	v1	FDI-09101538-0	Ralink RT3052F@384	32	4	Ralink	b/g/n	-	1
<u>WHR-G300N</u>	v2	FDI-09101561-0	Atheros AR7240@400	32	4	Atheros AR9283	b/g/n 2x2:2	-	1
<u>WHR-HP-AG108</u>	?	FDI-09101540-0	Atheros AR5312@220	32	4	Atheros	a/b/g/h	-	1
<u>WHR-HP-G300N</u>	?	FDI-09101621-0	Atheros AR7240@400	32	4	Atheros AR9283	b/g/n 2x2:2	-	1
<u>WHR-AMG54</u>	?	?	Broadcom BCM5352@200?	16?	4	Broadcom	a/b/g	?	?
<u>WHR-HP-G54</u>	-	FDI-09101577-0	Broadcom BCM5352@200	16	4	Broadcom	b/g	-	1
WHR-HP-GN	?	FDI-09101567-0	Atheros AR7240@400	32	4	Atheros AR9283	b/g/n 1x1:1	-	1
WHR2-A54G54	-	?	Broadcom ? @ ?	16?	4?	Broadcom	b/g?	-	?
WHR3-AG54	-	?	Broadcom BCM4704@264	64	4	Broadcom	a/b/g	1	1
WLA-G54	-	?	Broadcom BCM4702@125	16	4	Broadcom	b/g	1	-
WLA-G54C	-	?	Broadcom BCM4702@125	16	4	Broadcom	b/g	1?	?
WLA2-G54C	-	FDI-09101669-0	Broadcom BCM4712@200	16	4	Broadcom	b/g	-	1
WLA2-G54L	-	?	Broadcom BCM4702@125	16	4	Broadcom	b/g	-	1
WLAH-G54	-	?	Broadcom BCM4702@125	16	4	Broadcom	b/g?	-	1
WLI-CB-AG300N	-	?	Ralink RT2880F@266	32	4	Ralink	1x a/b/g/n 1x b/g	-	0
WLI-TX1-G54	-	?	Broadcom BCM5352@200	16	4	Broadcom	b/g?	-	?
WLI-TX4-G54HP	-	?	Broadcom BCM5352@200	16	4	Broadcom	b/g	-	?

Supported_Devices

WLI2-TX1-G54	-	?	Broadcom BCM5352@200	16	4	Broadcom	b/g	-	?
WLI3-TX1-G54	-	FDI-09101669-0	Broadcom BCM4712@200?	16	4	Broadcom	b/g	-	1
WVR-G54-NF	-	?	Broadcom ? @ ?	16?	4?	Broadcom	b/g	-	?
WZR-300HP		FDI-09101896-0	Atheros AR7242@400	64	32	Atheros AR9280	b/g/n 2x2:2	-	1
WZR-600DHP		FDI-09101889-0	Atheros AR7161@680	128	32	Atheros AR9220 + AR9223	a/n 2x2:2 b/g/n 2x2:2	-	1
WZR-600DHP2	-	FDI000000013	Broadcom BCM47081@800	256	128	Broadcom BCM43228 + BCM43217	a/n 2x2:2 b/g/n 2x2:2		
WZR-900DHP	-	FDI000000014	Broadcom BCM47081@800	256	128	Broadcom BCM4331 x 2	a/n 3x3:3 b/g/n 3x3:3		
WZR-1166DHP	-	FDI000000015	Broadcom BCM4708A0@800	256	128	Broadcom BCM4352 + BCM43217	2T2R a/c 866 b/g/n 300		
WZR-1750DHP	-	FDI000000009	Broadcom BCM4708@800	512	128	Broadcom BCM4360 + BCM4331	a/c 1300 b/g/n 450		
WZR-AGL300N	-	?	Ralink RT2880F@266	32	4	Ralink	1x a/b/g/n 1x b/g	-	0
WZR-D1100	-	Japan Model	Broadcom BCM4706@600	128	128	BCM 4360 + BCM4331	a/c 1300 b/g/n 450		
WZR-D1800H	-	FDI-09101695-0	Broadcom BCM4706@600	128	128	BCM 43460 + BCM4331	a/c 1300 b/g/n 450		

Supported_Devices

WZR-G54	-	- (Jpn model)	Broadcom BCM4704@264	16	4	Broadcom BCM4306	b/g	1	?
WZR-G144NH		- (Jpn model)	Broadcom BCM4785@300	32	4	Broadcom	b/g/n	-	-
<u>WZR-G300N</u>	-	FDI-09101466-0	Broadcom BCM4704@264	16/32	4	Broadcom	b/g/n	1	1
<u>WZR-HP-AG300H</u>	v1	FDI-09101592	Atheros AR7161@680	128	32	Atheros AR9220 + AR9223	a/n 2x2:2 b/g/n 2x2:2	-	1
WZR-HP-G54	-	FDI-09101457-0	Broadcom BCM4704@264	16	4	Broadcom BCM4306	b/g	1	1
<u>WZR-HP-G300NH</u>	v1	FDI-09101560-0	Atheros AR9132@400	64	32	Atheros AR9103	b/g/n 2x3:2	-	1
<u>WZR-HP-G300NH2</u>		FDI-09101896-0	Atheros AR7242@400	64	32	Atheros AR9280	b/g/n 2x2:2	-	1
WZR-HP-G301NH	v1	- (Jpn model)	Atheros AR9132@400	64	32	Atheros AR9103	b/g/n 2x3:2	-	1
WZR-HP-G302H		FDI-09101896-0	Atheros AR7242@400	64	32	Atheros AR9280	b/g/n 2x2:2	-	1
WZR-HP-G450H		FDI-09101912-0	Atheros AR7242@400	64	32	Atheros AR9381	b/g/n 3x3:3	-	1
WZR-RS-G54	?	FDI-09101457-0	Broadcom BCM4704@264	64	8	Broadcom BCM4306	b/g	1	1
WXR-1900DHP	-	-	Broadcom BCM4709@1000	512	128	-	a/c 1300 b/g/n 600	-	-

Conceptronic

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	I P c
C54APT	?	?	Atheros AR2312a@180	16	4	Atheros AR2112A	b/g	-	1	1	1 L

Supported_Devices

C300BRS4A	?	?	Ralink RT3052F@380	32	4	Ralink	b/g/n	-	1	-	4 L 1 W
C300BSR4	2.0	RRK-WRGN16	Ralink RT2880F@266	32	4	Ralink RT2820L	b/g/n	has pads	1	1	4 L 1 W

Cisco

- [see Linksys](#)

Compex

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Series por
MMC543	-	?	Atheros AR7130@300	32 (to 64)	4 (to 16)	1	a/h/n @ 23dbm	2	1
MMJ2N	-	?	Atheros AR7130@300	32	4	1	b/g/n @ 28dbm	2	1
MMJ5N	-	?	Atheros AR7130@300	32	4	1	a/h/n @ 28dbm	2	1
MMS2N	-	?	Atheros	32	4	1	b/g/n @	2	1

Supported_Devices

			AR7130@300				29dbm		
MMS5N	-	?	Atheros AR7130@300	32	4	1	a/h/n @ 29dbm	2	1
<u>NP18</u>	-	?	Xscale IXP42X@266-533	32-128	4-32	-	depends on card	2	1
<u>NP25G</u>	6A	?	Atheros AR2317@180	16	4	Atheros	b/g	-	1
NP27G	-	?	Infineon ADM5120@175	16	4	-	B/G	1	1
NP28G	-	?	Infineon ADM5120@175	32	4	-	B/G	1	1
WPE53G	?	TK4-08-WPE53G	Atheros AR2317@180	16	4	Atheros	b/g	-	?
WPE72	?	?	Atheros AR7240@400	32 (to 64)	4 (to 32)	-	-	1 (mPCIe)	1
WPE72NX	?	?	Atheros AR7240@400	32 (to 64)	4 (to 32)	-	a/b/g/h/n @ 21dBm	-	1
<u>WP18-6A</u>	1A	?	Xscale IXP42X@266	32	4	-	depends on card	2	1

Supported_Devices

<u>WP18-6B</u>	3B	?	Xscale IXP42X@533	64	8	-	depends on card	2	1
WPMA54- 2.4G14	-	?	Infineon ADM5120@175	16	4	-	depends on card	1	1
WPMA54- 5G17	-	?	Infineon ADM5120@175	16	4	-	depends on card	1	1
WPM54	-	?	Infineon ADM5120@175	16	4	-	depends on card	1	1
WP54-6E	6E	?	Infineon ADM5120@175	16	4	-	depends on card	1	1
WP54- 7A&C	7A or 7C	?	Infineon ADM5120@175	16	4	-	depends on card	1	1
WP54G	-	?	Infineon ADM5120@175	16	4	-	b/g	1	1
WP54AG	-	?	Infineon ADM5120@175	16	4	-	a/b/g/h	1	1
WPP54AG	-	?	Infineon ADM5120@175	32	4	-	a/b/g/h	1	1
WPP54G	-	?	Infineon ADM5120@175	32	4	-	b/g	1	1

Supported_Devices

<u>WP144</u>	-	?	Xscale IXP420@266	32	8	-	depends on card	2	1
<u>WP188- 6B</u>	-	?	Xscale IXP425@533	128	16	-	depends on card	4	1
<u>WP188- 6C</u>	6C	?	Xscale IXP425@533	64	8	-	depends on card	4	1
<u>WPM 188</u>	-	?	Xscale IXP425@533	64	8	-	2x a/b/g/h 2x B/G	4	1
<u>WP188MA- 2.4G14</u>	-	?	Xscale IXP425@533	64	8	-	2x a/b/g/h 2x B/G	4	1
<u>WP188MA- 5G17</u>	-	?	Xscale IXP425@533	64	8	-	2x a/b/g/h 2x B/G	4	1
<u>WP288</u>	6A (to 6C)	?	Atheros AR7161@680	32 (to 128)	4 (to 16)	-	-	3	1

Supported_Devices

WP543	6C (to 6H)	?	Atheros AR7130@300	32	4 (to 16)	-	depends on card	1 (to 2)	1
WP543A-6ANX	-	?	Atheros AR7130@300	16	4	1	a/b/g/h/n @ 20dbm	2	1
WP543AHV	?	?	Atheros AR71610@680	32 (to 64)	8 (to 16)	-	depends on card	2	1
WP546HV	-	?	Atheros AR7161@680	64	8	-	depends on card	2	1
WPJ72	?	?	Atheros AR7240@400	32 (to 64)	4 (to 16)	-	a/n @ 29dBm	-	1
WPJ72R5N29	?	?	Atheros AR7240@400	32 (to 64)	8 (to 16)	-	depends on card	1 PCIe	1
WPJ543	6C	?	Atheros AR7130@300	32	4 (to 16)	-	depends on card	1 (to 2)	1
WPMN543-5G16dBi	-	?	Atheros AR7130@300	32	4	1	a/b/g/h/n	2	1
WPP543A-7CNX	-	?	Atheros AR7130@300	16	4	1	a/b/g/h/n	2	1

Supported_Devices

Conrad Elektronik

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]	Sp Fea N
N150	?	?	Ralink RT3050F@320	32	4	Ralink	b/g/n	-			1 LAN	5V/2A?	1 U 2.0

Corega

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port
CG-WLBARGS	-	RRK-WRGG15CA1	Atheros AR2315A	16	4	SOC	b/g	-	1	?
CG-WLBARN20	-	U2M-SR97908003	Ralink RT3052@384	32	4	SOC	b/g/n	-	1	?
CG-WLBARN23	Rev. A	?	Ralink RT2880F@266	16	4	Ralink RT2820L	b/g/n	-	?	?
CG-WLBARN50	-	U2M-SR97908001	Ralink RT2880F@266	32	4	Ralink RT2820	b/g/n	-	1	?
CG-WLBARN80	v1.1.1	U2M-SR97908002	Ralink RT2880@266	32	4	Ralink RT2820	b/g/n	-	1	?
CG-WLCVRG	?	?	Atheros AR2312@180	16	4	Atheros	b/g	-	?	?

Dell

Model	H.W. rev	FCC ID	Platform & Frequency	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard	mini PCI	Serial port	J
-------	----------	--------	----------------------	----------	------------	--------------	---------------	----------	-------------	---

Supported_Devices

			[MHz]				[802.11]			
<u>TrueMobile 2300 Model WX-5565D</u>	vA00 or A01	MXF-R920401G	Broadcom BCM4710@125	16	4	Broadcom	b/g	1	?	ac pc
<u>TrueMobile 2300 Model WX-5565D</u>	v1	MXF-R920401G	Broadcom BCM4710@125	16	4	Broadcom	b/g	1	?	ac pc
<u>TrueMobile 2300 Model WRTB-107GD340</u>	vA00 or v2	MXF-R921212G	Broadcom BCM4712@200	16	4	Broadcom	b/g	-	?	1

Devolo

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]	Spe Fe
dLAN 200 AVpro Host	?	?	Xscale IXP420@266	32	8	-	-	1	1	1	4 LAN	5V 1.2A?	Po Ro
dLAN 200 AV WirelessG	?	?	Xscale IXP420@266	32	4	1	b/g	1	1	1	4 LAN	5V 1.2A?	Po Ro

Digitus

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]	Speci Featu Not
DN-15017	?	?	Ralink RT3052@380	32	4	-	-	1	1	1	3 LAN	5V 1.2A?	Power Route

Supported_Devices

D-Link

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTA po
DIR-300	A1	KA2DIR300A1	Atheros AR2317@182	16	4	Atheros	b/g	-	?	1
<u>DIR-300</u>	B1	KA2DIR300B1	Ralink RT3050@320	32	4	Ralink	b/g/n	-	?	1
DIR-320	A1	KA2DIR320A1	Broadcom BCM5354@240	32	4	Broadcom BCM4318	b/g	-	?	1
DIR-320	A2	KA2DIR320A1	Broadcom BCM5354@240	32	4	Broadcom BCM4318	b/g	-	?	1
<u>DIR-330</u>	A1	KA2DIR330A1	Broadcom BCM5836@264	32	8	Broadcom	b/g	1	1	1
DIR-400	A1	KA2IR400A1	Atheros AR2318@182	16	4	Atheros	b/g	-	1	1
DIR-412	A1	KA2IR412A1	Ralink RT3050F@320	32	4	Ralink	b/g/n	-	1	-
DIR-600	A1	KA2DIR600A1	Atheros AR7240@400	32	4	Atheros AR9285	b/g/n 1x1:1	-	Yes	Yes
DIR-600	B1 B2	KA2DIR300B1	Ralink RT3050F@320	32	4	Ralink	b/g/n	-	1	?
DIR-601	A1	KA2DIR601A1	Atheros AR7240@400	32	4	Atheros AR9285	b/g/n 1x1:1	-	Yes	Yes
DIR-601	B1	KA2IR601B1	Atheros AR9331@400	32	4	SOC	b/g/n 1x1:1	-	Yes	Yes
DIR-605	D1	KA2DIR605D1	Broadcom BCM4716@300	32	4	Broadcom	b/g/n	-	1	1
<u>DIR-615</u>	C1	KA2DIR615C1	Atheros AR9130@400	32	4	Atheros AR9102	b/g/n 2x2:2	-	Yes	Yes
<u>DIR-615</u>	C2	KA2DIR615C1	Atheros AR9130@400	32	4	Atheros AR9102	b/g/n 2x2:2	-	Yes	Yes
<u>DIR-615</u>	D1	KA2DIR605B1	Ralink RT3052F@384	32	4	Ralink	b/g/n	-	1	?
<u>DIR-615</u>	D2	KA2DIR605B1	Ralink RT3052F@384	32	4	Ralink	b/g/n	-	1	?

Supported_Devices

<u>DIR-615</u>	D3	KA2DIR605B1	Ralink RT3052F@384	32	4	Ralink	b/g/n	-	1	?
<u>DIR-615</u>	D4	KA2DIR605B1	Ralink RT3052F@384	32	4	Ralink	b/g/n	-	1	?
<u>DIR-615</u>	E1	KA2IR615E1	Atheros AR7241@400	32	4	Atheros AR9283	b/g/n 2x2:2	-	Yes	Yes
<u>DIR-615</u>	E3/E4	KA2IR615E3	Atheros AR7240@400	32	4	Atheros AR9287	b/g/n 2x2:2	-	Yes	Yes
DIR-615	H1/H2	KA2IR615H1	Ralink RT3352F@400	32	4	SOC 2T2R	b/g/n	-	Yes	Yes
DIR-615	I1	KA2IR615I1	Atheros AR9341@535	32	4	SOC	b/g/n 2x2:2	-	Yes	Yes
DIR-615	I2	KA2IR615I1	Atheros AR9341@535	32	4	SOC	b/g/n 2x2:2	-	Yes	Yes
DIR-615	I3	KA2IR615I3	Atheros AR9341@535	32	4	SOC	b/g/n 2x2:2	-	Yes	Yes
DIR-620	B1	KA2DIR615G1	Ralink RT3052F@384	32	8	Ralink	b/g/n	-	1	?
<u>DIR-632</u>	A1	KA2IR632A1	AR7241 or AR7242@400	32	8	Atheros AR9287	b/g/n 2x2:2	-	1	?
DIR-810L	A1	KA2IR810LA1	Mediatek MT7620A@580	64	8	SOC + MT7610E	b/g/n 2x2:2 ac/an 1x1:1	-	1	?
DIR-810L	B1	KA2IR810LB1	Mediatek MT7620A@580	64	8	SOC + MT7610E	b/g/n 2x2:2 ac/an 1x1:1	-	1	?
<u>DIR-825</u>	B1	KA2DIR825B1	Atheros AR7161r2@680	64	8	Atheros AR9220 + AR9223	a/n 2x2:2 b/g/n 2x2:2	-	1	1
<u>DIR-825</u>	B2	KA2DIR825B1	Atheros AR7161r2@680	64	8	Atheros AR9220 + AR9223	a/n 2x2:2 b/g/n 2x2:2	-	1	1
DIR-825	C1	KA2IR825C1	AR9344@560	128	16	SOC+Atheros AR9382	b/g/n 2x2:2 a/n 2x2:2	-	1	1
DIR-835	A1	KA2IR835A1	AR9344@560	128	16			-	1	1

Supported_Devices

						SOC+Atheros AR9380	b/g/n 2x2:2 a/n 3x3:3			
DIR-860L	A1	KA2IR860LA1	BCM47081@800	128	128	BCM4352 + BCM43217	a/c 900 b/g/n 300	1	1	1
DIR-860L	B1	KA2IR860LB1	Mediatek MT7621AT@880	128	128	MT7612E + MT7602E	a/c 900 b/g/n 300	1	1	1
DIR-868L	A1	KA2IR868LA1	BCM4708@800	128	128	Broadcom BCM43460 + BCM4331	a/c 1300 b/g/n 450	1	1	1
DSM-G600	rev A	?	Xscale IXP420@266	64	16	atheros	b/g	?	1	1
<u>DWL-2100</u>	A1 - A4		Atheros AR2312a@180	16	4	Atheros	b/g	-	1	1

Doodle Labs

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]	Sp Fea N
DLM101	?	?	Atheros ? @ 180?	16?	4	Atheros	b/g@24dbm	-	-	-	1 LAN WAN	?	?

Dynex

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port
DX-NRUTER	-	K7SDXNRUTER	Broadcom BCM4703@264	32	4	Broadcom	b/g/n	-	Yes	Yes

Edimax

Model	H.W. rev	FCC ID	Platform & Frequency	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard	mini PCI	Serial port	JTAG port
-------	----------	--------	----------------------	----------	------------	--------------	---------------	----------	-------------	-----------

Supported_Devices

			[MHz]				[802.11]			
BR-6224N	?	NDD9562240922	Ralink RT3050@320	16	4	Ralink	b/g/n	-	-	-
BR-6226N	?	NDD9562250817	Ralink RT3050@320	16?	4	Ralink	b/g/n	-	-	-
BR-6574N	A	NDD9565740806	Ralink RT2880F@266	16	4	Ralink RT2820L	b/g/n	-	-	-
EW-7303APn / EW-7303HPn	v2	NDD9573031016	Ralink RT3350(marked as RT3050F)@320	32	4	Ralink	b/g/n 1T1R	-	-	-

Encore

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port
ENHWI-2AN3	-	U2M-SR97908003	Ralink RT3052@384	32	4	Ralink	b/g/n	-	1	
ENHWI-N2	A1 A2 B1	NHPWLN2206	Atheros AR9130@400	32	4	Atheros AR9102	b/g/n 2x2:2	-	Yes	Yes
ENHWI-N3	-	U2M-SR97908005	Ralink RT3050F@320	16	4	Ralink	b/g/n	-	1	

EnGenius

- [see Senao](#)

Exel Networks

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port
ExelLent/ExelMed/ExelMin Series	-	?	Xscale IXP425@533	64	8?	Atheros AR5006X	1-4x a/b/g/h @ 22-28dBm	2	1	1

Fluidmesh

Model	H.W. rev	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	Power Input [V]	Spec Features/Notes
<u>2200 Duo</u>	-	Geode LX @ 433-500?	128-256?	depends on cf card	2	a/b/g/h @ 18dBm	2	1	-	2	yes	7- 18	outdoor enclosure, hardware watchdog, temperature sensor
<u>2200 Endo</u>	-	Geode LX @ 433-500?	128-256?	depends on cf card	2	a/b/g/h @ 18dBm	2	1	-	2	yes	7- 18	hardware watchdog, temperature sensor
<u>2200 Duo</u>	-	Geode LX @ 433-500?	128-256?	depends on cf card	2	a/b/g/h @ 18dBm	2	1	-	2	yes	7- 18	outdoor enclosure, 13dBi @ 2.4GHz, 15dBi @ 5GHz, hardware watchdog, temperature sensor

Supported_Devices

FON

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
<u>La Fonera</u>	2100	HED-FON2100	Atheros AR2315@180	16	8	Atheros	b/g	-	1	?	1 WAN
<u>La Fonera</u>	2200	UVA-FON2200	Atheros AR2315@180	16	8	Atheros	b/g	-	1	?	1 WAN
<u>La Fonera+</u>	2201	UVA-FON2201	Atheros AR2315A@180	16	8	Atheros	b/g	-	1	?	1 LAN 1 WAN
<u>La Fonera 2.0g</u>	2202	UVA-FON2201	Atheros AR2315A@180	32	8	Atheros	b/g	-	1	?	1 LAN 1 WAN
<u>La Fonera 2.0n</u>	2303	NDD9564250816	Ralink RT3052F@384	64	8	Ralink	b/g/n	-	1	?	4 LAN 1 WAN

Fry's Electronics

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
FR-54RTR	A1	KA2DIR600A1	Atheros AR7240@400	32	4	Atheros AR9285	b/g/n 1x1:1	-	Yes	Yes	4 LAN 1 WAN
FR-300RTR	A1	KA2IR615E1	Atheros AR7241@400	32	4	Atheros AR9287	b/g/n 2x2:2	-	Yes	Yes	4 LAN 1 WAN

Gateway

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]	Spec Features Note
-------	----------	--------	----------------------------	----------	------------	--------------	------------------------	----------	-------------	-----------	-----------------	-------------------	--------------------

Supported_Devices

7001	-	?	Xscale IXP420@266	32	8	Atheros	a/b/g/h	2	1	1	1 LAN	?	a/g or version
------	---	---	----------------------	----	---	---------	---------	---	---	---	----------	---	-------------------

Gateworks

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. cou
Avila GW2343	-	-	Xscale IXP425@533	64	16	-	depends on card	4	1	?	4 LAN WAN
<u>Avila GW2345</u>	-	-	Xscale IXP425@533	64	16	-	depends on card	4	1	?	4 LAN WAN
<u>Avila GW2347</u>	-	-	Xscale IXP420@266	32	8	-	depends on card	1	with GW 16027 JTAG Serial Adapter	yes	1 LAN
<u>Avila GW2348-2</u>	-	-	Xscale IXP420@266	32	8	-	depends on card	2	1	Yes	1 LAN WAN
<u>Avila GW2348-4</u>	-	-	Xscale IXP425@533	64	16	-	depends on card	4	1	Yes	1 LAN WAN
<u>Avila GW2348- 4LIGHT</u>	-	-	Xscale IXP420@400	32	8	-	depends on card	4	1	Yes	1 LAN WAN

Supported_Devices

<u>Cambria GW2350</u>	-	-	Xscale IXP435@667	128	32	-	depends on card	1	1	Yes	1 LAN WAN
<u>Avila GW2353</u>	-	-	Xscale IXP425@533	64	64	-	depends on card	2	1	Yes	1 LAN WAN
<u>Avila GW2355</u>	-	-	Xscale IXP425@533	64	16	-	depends on card	4	1	Yes	4 LAN WAN
<u>Avila GW2357</u>	-	?	Xscale IXP422@266	32	16	-	depends on card	1	1	?	1 LAN WAN
<u>Cambria GW2358-4</u>	-	-	Xscale IXP435@667	128	32	-	depends on card	4	1	Yes	1 LAN WAN
<u>Cambria GW2369</u>	-	-	Xscale IXP435@667?	128?	32?	-	depends on card	4?	1	Yes	1 LAN WAN
Laguna GW2380	-	-	Cavium ECONA CN3411@300	128	16	-	depends on card	1 (mPCIe)	2	Yes	1 (Gbi LAN V
Laguna GW2382	-	-	Cavium ECONA CN3411@300	128	16	-	depends on card	1 (mPCIe)	2	Yes	1 (Gbi LAN V
	-	-		128	16	-		1 (mPCIe)	2	Yes	

Supported_Devices

Laguna GW2383			Cavium ECONA CN3411@300				depends on card						1 (Gbi LAN V
Laguna GW2387	-	-	Cavium ECONA CN3411@300	256	16	-	depends on card	1 (mPCIe)	2	Yes			1 (Gbi LAN V
Laguna GW2388-4	-	-	Cavium ECONA CN3420@2x600	256	16	-	depends on card	4	2	Yes			2 (Gbi LAN V
Laguna GW2389	-	-	Cavium ECONA CN3420@2x600	256	16	-	depends on card	2 (not kown now) + 2 (mPCIe)	2	Yes			1 (Gbi LAN V
Laguna GW2391	-	-	Cavium ECONA CN3410@300	256	16	-	depends on card	2 (miniPCIe)	2	Yes			1 (Gbi LAN/V

Guest Internet Solutions

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	Power Input [V/A]
<u>GIS-R5</u>	-	-	Atheros AR7161@680	64	16	-	depends on card	3	1	yes	2 LAN 1 WAN	yes	5- 24
<u>GIS-R6</u>	-	-	Atheros AR7161@680	64	16	-	depends on card	3	1	yes	2 LAN 1	yes	5- 24

Supported_Devices

													WAN		
<u>GIS-R10</u>	-	-	Atheros AR7161@680	64	16	-	depends on card	3	1	yes			2 LAN 1 WAN	yes	5- 24

Hame

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]
A15	-	?	Ralink RT5350F@	32	4	Ralink	b/g/n 1T1R	-	?	-	1 LAN/WAN	via Micro-USB

Intellinet (Reichelt)

- [see RFNet Technologies](#)

lomega

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]	Sp Fe N
NAS100d	-	?	Xscale IXP420@266	64	16	Atheros	B/G	1	1	?	1 LAN	?	1 p usb

JJPlus

Model	H.W. rev	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE
-------	----------	----------------------------	----------	------------	--------------	------------------------	----------	-------------	-----------	-----------------	-----

Supported_Devices

AC622	-	Atheros AR7240@400	32	8	-	?	-	1	1	? LAN WAN	yes	1
AC722	-	Atheros AR7240@400	32	8	-	?	-	1	1	? LAN WAN	yes	1
<u>JA76PF</u>	-	Atheros AR7161@680	64	8	-	depends on card	3	1	1	4 LAN 1 WAN	yes	8 & 4
JJAP93	-	Atheros AR7240@400	32	8	-	?	-	1	1	? LAN WAN	yes	1
<u>JWAP003</u>	-	Atheros AR7130@300	32	8	-	depends on card	1	1	1	2 LAN WAN	yes	1
JWAP501	-	Atheros AR7240@400	32	8	-	?	-	1	1	? LAN WAN	yes	1
<u>JWAP005</u>	-	Atheros AR7240@400	64	8	Atheros AR9285@27dBm	b/g/n 1x1:1	-	1	1	4 LAN/1 WAN	yes	1

Lanready

Model	H.W. rev	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
FN2-A3H5	-	Atheros AR2315@180	16	4	-	b/g @ 27dbm	1	1	1	1 LAN WAN

Supported_Devices

FN3A	-	Atheros AR7120@400	16-64	8-16	Atheros AR9285@18dbm	b/g/n 1x1:1	1	1	1	3 LAN WAN	8	
FN3AH5	-	Atheros AR7120@400	16-32	4-8	-	a/h/n AR9280 @ 27dbm	1	1	1	2 LAN WAN	8	
FN5-11P	-	Xscale IXP420@266 IXP425@533	32/64	8/16	-	depends on card	1	1	1	2 LAN WAN	y	
FN5-22P	-	Xscale IXP420@266	64	16	-	depends on card	2	1	1	2 LAN WAN	y	
FN5-22Pv2	-	Xscale IXP425@533	64	16	-	depends on card	2	1	1	2 LAN WAN	y	
FN5-42F	-	Xscale IXP425@533	64	16	-	depends on card	2	1	1	2 LAN WAN	y	
FN5-42FN	-	Xscale IXP425@533	32 64 128	8 16	-	depends on card	4	1	1	2 LAN WAN	y	
FN5-42P	-	Xscale IXP425@533	64	16	-	depends on card	4	1	1	2 LAN WAN	y	
FN5-45P-V2	-	Xscale IXP425@533	64	16	-	depends on card	2	1	1	5 LAN WAN	y	
WDR800F	-	Xscale IXP425@533	64	16	-	depends on card	4	1	?	2 LAN	y	

Supported_Devices

												WAN
WDR802F	-		Xscale IXP425@266?	64	16	-		depends on card	2	1	?	2 LAN WAN
WDR802F	-		Xscale IXP425@533	64	16	-		depends on card	4	1	?	2 LAN WAN
WDR2000	SCD0059		Xscale IXP425@266	64	16	-		depends on card	2	1	?	2 LAN WAN

Linksys (a devision of Belkin - formerly Cisco)

Linksys (Wired)

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Ant. Conn. Type	WLAN NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
<u>NSLU2</u>	-	?	Xscale IXP420@133-266	32	8	-	-	-	-	2 USB, Mod to add RS- 232	Mod to add	1
<u>RVS4000</u>	1.0	?	Star Semiconductor STR9202	64	8	-	-	-	-	-	1	4 LAN 1 WAN
<u>RV042</u>	1.0	?	Xscale IXP425@266	32	8	-	-	-	-	1	1	4 LAN 2 WAN
<u>RV082</u>	1.0	?	Xscale IXP425@533	32	16	-	-	-	-	1	1	8 LAN 2 WAN

Supported_Devices

Linksys (Wireless a/b/g/n)

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Ant. Conn. Type	WLAN NIC	WLAN standard [802.11]
E800	1.0	Q87-E800	Broadcom BCM5357C0@300	32	8	Internal	Broadcom	b/g/n
E900	1.0	Q87-E900	Broadcom BCM5357C0@300	32	8	Internal	Broadcom	b/g/n
<u>E1000</u>	1.0	Q87-E1000	Broadcom BCM4716B0@300	32	4	Internal	Broadcom	b/g/n
<u>E1000</u>	2.0	Q87-E1000V2	Broadcom BCM5357B0@300	32	4	Internal	Broadcom	b/g/n
<u>E1000</u>	2.1	Q87-E1000V21	Broadcom BCM5357B0@300	32	4	Internal	Broadcom	b/g/n
<u>E1200</u>	1.0	Q87-E1200	Broadcom BCM5357B0@300	32	4	Internal	Broadcom	b/g/n
<u>E1200</u>	2.0	Q87-E1200V2	Broadcom BCM5357C0@300	32	8	Internal	Broadcom	b/g/n
E1500	1.0	Q87-E1500	Broadcom BCM5357B0@300	32	8	Internal	Broadcom	b/g/n
E1550	1.0	Q87-E1550	Broadcom BCM5358UB0@300	64	16	Internal	Broadcom	b/g/n
E1700	1.0	Q87-E1700	Mediatek MT7620A@580	32	8	External	SOC	b/g/n 2x2:2
<u>E2000</u>	1.0	Q87-E2000	Broadcom BCM4717A1@354	32	8	Internal	Broadcom	a/b/g/n

Supported_Devices

<u>E2100L</u>	1.0	Q87-E2100L	Atheros AR9130@400	64	8	-	Atheros AR9102	b/g/n 2x2:2
E2500	1.0	Q87-E2500	Broadcom BCM5358UB0@300	64	8	Internal	SOC + Broadcom BCM43236	a/b/g/n
<u>E3000</u>	1.0	Q87-E3000	Broadcom BCM4718A1@480	64	8	Internal	Broadcom	a/b/g/n
<u>E3200</u>	1.0	Q87-E3200	Broadcom BCM5357r1@500	64	16	Internal	SOC + Broadcom BCM43236	a/b/g/n
<u>E4200</u>	1.0	Q87-E4200	Broadcom BCM4718A1@480	64	16	Internal	Broadcom	a/b/g/n
EA2700	1.0	Q87-EA2700	Broadcom BCM5358U@480	64	64	Internal	SOC + Broadcom BCM43236	a/b/g/n
EA6200	1.0	Q87-EA6200	Broadcom BCM47081A0@800	128	128	Internal	BCM4352 + BCM43217	a/c 600 b/g/n 300
EA6300	no version	Q87-EA6300	Broadcom BCM47081A0@800	128	128	Internal	BCM4352 + BCM43217	a/c 900 b/g/n 300
EA6300	1.0	Q87-EA6400	Broadcom BCM4708A0@800	128	128	Internal	BCM4360 + BCM43217	a/c 1300 b/g/n 300
EA6400	1.0	Q87-EA6400	Broadcom BCM4708A0@800	128	128	Internal	BCM4360 + BCM43217	a/c 1300 b/g/n 300
EA6500	1.0	Q87-EA6500	Broadcom BCM4706@600	128	128	Internal	BCM4360 + BCM4331	a/c 1300 b/g/n 450
EA6500	2.0	Q87-EA6500v2		256	128	Internal		

Supported_Devices

			Broadcom BCM4708A0@800				BCM4360 + BCM4331	a/c 1300 b/g/n 450
EA6700	1.0	Q87-EA6700	Broadcom BCM4708A0@800	256	128	Internal	BCM4360 + BCM4331	a/c 1300 b/g/n 450
EA6900	1.0	Q87-EA6900	Broadcom BCM4708A0@800	256	128	Internal	BCM4360 x2	a/c 1300 b/g/n 600
<u>WRT150N</u>	1.0	Q87-WRT150N	Broadcom BCM4704@264	16	4	Fixed	Broadcom	b/g/n
<u>WRT150N</u>	1.1	Q87-WRT150NV11	Broadcom BCM4704@264	16	4	Fixed	Broadcom	b/g/n
<u>WRT160N</u>	1.0	Q87-WRT160N	Broadcom BCM4704@264	16	4	Internal	Broadcom	b/g/n
<u>WRT160N</u>	1.1	Q87-WRT160NV11	Broadcom BCM4704@264	16	4	Internal	Broadcom	b/g/n
<u>WRT160N</u>	2.0	Q87-WRT160NV2	Ralink RT2880F@266	16	4	?	Ralink	b/g/n
<u>WRT160N</u>	3.0	Q87-WRT160NV3	Broadcom BCM4716A@300	32	4	Internal	Broadcom	b/g/n
<u>WRT160NL</u>	1.0	Q87-WRT160NL	Atheros AR9130@400	32	8	RP-SMA	Atheros AR9102	b/g/n 2x2:2
<u>WRT300N</u>	1.0	Q87-WRT300N	Broadcom BCM4704@264	32	4	Fixed	Broadcom	b/g/n
<u>WRT300N</u>	1.1	Q87-WRT300NV11	Broadcom BCM4785@300	32	8	Fixed	Broadcom	b/g/n

Supported_Devices

<u>WRT300N</u>	2.0	Q87-WRT300NV2	Xscale IXP422@266	16	4	Fixed	Atheros	b/g/n
<u>WRT310N</u>	1.0	Q87-WRT310N	Broadcom BCM4785@300	32	4	Internal	Broadcom	b/g/n
<u>WRT310N</u>	2.0	Q87-WRT310N	Broadcom BCM4716@300	32	4	Internal	Broadcom	b/g/n
<u>WRT320N</u>	1.0	Q87-WRT320N	Broadcom BCM4717A@354	32	8	Internal	Broadcom	b/g/n
<u>WRT350N</u>	1.0 CNQ	Q87-WRT350N	Broadcom BCM4785@300	32	8	Fixed	Broadcom	b/g/n
<u>WRT400N</u>	1.0	Q87-WRT400N	Atheros AR7161@680	32	8	Internal	Atheros	a/b/g/n
<u>WRT600N</u>	1.0	Q87-WRT600NV1	Broadcom BCM4705@300	32	8	Fixed	Broadcom	a/b/g/n
<u>WRT600N</u>	1.1	Q87-WRT600NV11	Broadcom BCM4785@300	32	8	Fixed	Broadcom	a/b/g/n
<u>WRT610N</u>	1.0	Q87-WRT610N	Broadcom BCM4705@300	64	8	Internal	Broadcom	a/b/g/n
<u>WRT610N</u>	2.0	Q87-WRT610NV2	Broadcom BCM4718@480	64	8	Internal	Broadcom	a/b/g/n

Linksys (Wireless a/b/g)

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Ant. Conn. Type	WLAN NIC
-------	-------------	--------	----------------------------------	-------------	---------------	--------------------	----------

Supported_Devices

<u>WAP54G</u>	1.0	PKW-WAP54G	Broadcom BCM4702@125	8 or 16	2 or 4	RP- TNC	Broadcom BCM4306	ba
<u>WAP54G</u>	1.1	PKW-WAP54G	Broadcom BCM4702@125	8 or 16	2 or 4	RP- TNC	Broadcom BCM4306	ba
<u>WAP54G</u>	2.0	Q87-WAP54GV2	Broadcom BCM4712@200	8	2	RP- TNC	Broadcom SoC	ba
<u>WAP54G</u>	3.0	Q87-WAP54GV3	Broadcom BCM5352@200	8	2	RP- TNC	Broadcom SoC	ba
<u>WAP54G</u>	3.1	Q87-WAP54GV31	Broadcom BCM5352@200	8	2	RP- TNC	Broadcom SoC	ba
<u>WRE54G</u>	v1	Q87-WRE54G	Broadcom BCM4712@200	8	2	RP- TNC	Broadcom SoC	ba
<u>WRH54G</u>	?	Q87-WRH54G	Broadcom BCM5354@240	8	2	RP- TNC	Broadcom SoC	ba
<u>WRT51AB</u>	1.0	PKW-WRT51AB	Broadcom BCM4702@125	32	4	Fixed	Broadcom BCM4301+ Atheros AR5000	ba
<u>WRT54G</u>	1.0	PKW-WM54G	Broadcom BCM4710@125	16	4	RP- TNC	Broadcom BCM4306	ba
<u>WRT54G</u>	1.1	Q87-WRT54G11	Broadcom BCM4710@125	16	4	RP- TNC	Broadcom BCM4306	ba
<u>WRT54G</u>	2.0	Q87-WRT54GV2	Broadcom BCM4712@200	16	4	RP- TNC	Broadcom BCM2050KML	ba
<u>WRT54G</u>	2.2	Q87-WT54GV22	Broadcom BCM4712@216	16	4	RP- TNC	Broadcom BCM2050KML	ba
<u>WRT54G</u>	3.0	Q87-WT54GV22	Broadcom BCM4712@216	16	4	RP- TNC	Broadcom BCM2050KML	ba
<u>WRT54G</u>	3.1	?	Broadcom BCM4712@216	16	4	RP- TNC	Broadcom BCM2050KML	ba
<u>WRT54G</u>	4.0	Q87-WT54GV40	Broadcom BCM5352@200	16	4	RP- TNC	Broadcom SoC	ba
<u>WRT54G</u>	5.0	Q87-WRT54GV5	Broadcom BCM5352@200	8	2	RP- TNC	Broadcom SoC	ba
<u>WRT54G</u>	5.1	?	Broadcom BCM5352@200	8	2	RP- TNC	Broadcom SoC	ba
<u>WRT54G</u>	6.0	Q87-WT54GV60	Broadcom BCM5352@200	8	2	RP- TNC	Broadcom SoC	ba
<u>WRT54G</u>	7.2	?	Broadcom BCM5354@240	8	2	RP- TNC	Broadcom SoC	ba
<u>WRT54G</u>	8.0	Q87-WRT54GV8	Broadcom BCM5354@240	8	2	Fixed	Broadcom SoC	ba
<u>WRT54G</u>	8.1	Q87-WRT54GV81	Broadcom BCM5354@240	8	2	Fixed	Broadcom BCM5354 SoC	ba

Supported_Devices

<u>WRT54G</u>	8.2	Q87-WRT54GV82	Broadcom BCM5354@240	8	2	Fixed	Broadcom SoC	b
<u>WRT54G2</u>	1.0	Q87-WRT54G2V1	Broadcom BCM5354@240	16	2	Internal	Broadcom SoC	b
<u>WRT54G2</u>	1.1	?	Atheros AR2317@180	16	4	Internal	Atheros	b
<u>WRT54G2</u>	1.3	Q87-WRT54G2V13	Broadcom BCM5354@240	8	2	Internal	Broadcom SoC	b
<u>WRT54GL</u>	1.0 1.1	Q87-WT54GV40	Broadcom BCM5352@200	16	4	RP- TNC	Broadcom SoC	b
<u>WRT54G-LA</u>	8.0	Q87-WRT54GV8	Broadcom BCM5354@240	8	2	Fixed	Broadcom SoC	b
<u>WRT54G-RG</u>	?	Q87-WT54GV40	Broadcom BCM5352@200	32	8	RP- TNC	Broadcom SoC	b
<u>WRT54G-TM</u>		Q87-WT54GV40	Broadcom BCM5352@200	32	8	RP- TNC	Broadcom SoC	b
<u>WRT54GS</u>	1.0	Q87-WRT54GV2	Broadcom BCM4712@200	32	8	RP- TNC	Broadcom BCM2050KML	b
<u>WRT54GS</u>	1.1	Q87-WT54GV22	Broadcom BCM4712@200	32	8	RP- TNC	Broadcom BCM2050KML	b
<u>WRT54GS</u>	2.0	Q87-WT54GV22	Broadcom BCM4712@200	32	8	RP- TNC	Broadcom BCM2050KML	b
<u>WRT54GS</u>	2.1	?	Broadcom BCM4712@216	32	8	RP- TNC	Broadcom BCM2050KML	b
<u>WRT54GS</u>	3.0	Q87-WT54GV40	Broadcom BCM5352@200	32	8	RP- TNC	Broadcom SoC	b
<u>WRT54GS</u>	4.0	Q87-WT54GV40	Broadcom BCM5352@200	16	4	RP- TNC	Broadcom SoC	b
<u>WRT54GS</u>	5.0	Q87-WT54GV40	Broadcom BCM5352@200	16	2	RP- TNC	Broadcom SoC	b
<u>WRT54GS</u>	5.1	Q87-WT54GV40	Broadcom BCM5352@200	16	2	RP- TNC	Broadcom SoC	b
<u>WRT54GS</u>	6.0	Q87-WT54GV60	Broadcom BCM5352@200	16	2	RP- TNC	Broadcom SoC	b
<u>WRT54GS</u>	7.0	Q87-WRT54GSV7	Broadcom BCM5354@240	16	2	RP- TNC	Broadcom SoC	b
<u>WRT54GS</u>	7.2	Q87-WRT54GSV72	Broadcom BCM5354@240	16	2	RP-TNC/Fixed	Broadcom SoC	b
<u>WRT54GS2</u>	1.0	Q87-WRT54G2V1	Broadcom BCM5354@240	8	2	Internal	Broadcom SoC	b
<u>WRT54GX</u>	1.0	Q87-WRT54GX		16	4	RP- TNC	?	b

Supported_Devices

			Broadcom BCM4704@266						
<u>WRT54GP2A-AT</u>	?	Q87-WRV54GP2M	Xscale IXP425@400	32	8	?		Inprocomm	b/
<u>WRT55AG</u>	1.0	PKW-WRT55AG	Broadcom BCM4702@125	32	4	Fixed		Broadcom BCM4306 + Atheros AR5002A	a/
<u>WRT55AG</u>	2.0	Q87-WRT55AGV2	Atheros AR5312@230	16	4	Fixed		Atheros	a/
WRV54G	?	Q87-WRV54G	XScale IXP425@266	32	8	1		Prism (must be replaced)	b/
<u>WRTSL54GS</u>	all	Q87-WTSLGS	Broadcom BCM4704@266	32	8	Single Fixed		Broadcom BCM4318	b/
<u>WTR54GS</u>	1.0	Q87-WTR54GS	Broadcom BCM5350@200	16	4	Internal		Broadcom SoC	b/
<u>WTR54GS</u>	2.0	Q87-WTR54GS	Broadcom BCM5350@200	8	2	Internal		Broadcom SoC	b/
<u>WTR54GS</u>	2.1	Q87-WTR54GSV21	Broadcom BCM5350@200	8	2	Internal		Broadcom SoC	b/

Linksys Valet

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Ant. Conn. Type	WLAN NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port
<u>M10</u>	v 1.0	Q87-M10	Broadcom BCM4716A@300	32	4	Internal	Broadcom	b/g/n	-	1	?
<u>M10</u>	v 2.0	Q87-M10V2	Broadcom BCM5357@300	32	4	Internal	Broadcom	b/g/n	-	1	?

Supported_Devices

M20	v 1.0	Q87-M10V2	Broadcom BCM4716@300	32	4	Internal	Broadcom	b/g/n	-	1	?
-----	-------	-----------	-------------------------	----	---	----------	----------	-------	---	---	---

Logilink

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port
WL0129		NDD9573031016	Ralink RT3350(marked as RT3050F)@320	32	4	Ralink	b/g/n 1T1R	-	-	-	2 LAN

MagicBox

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE
<u>MagicBox 1.1</u>	-	?	PowerPC@200	32	4	-	depends on card	1	1	?	1 LAN	yes
<u>MagicBox 2.0</u>	-	?	PowerPC@266-333	32	4	-	depends on card	3	^	?	1 LAN 1 WAN	yes

Meraki

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port
<u>Mini</u>	-	UDX-MERAKI-MINI	Atheros AR2315@180	32	8	Atheros	b/g	-	1	1	1 LAN
	-	UDX-MERAKI-OTDR		32	8	Atheros	b/g	-	1	1	

Supported_Devices

												19)	
<u>RB-1000</u>	-	-	Freescale PPC MPC8548 @ 1333	512	64	-	-	-	1	?	3 LAN WAN	yes	

Mitsubishi

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]	S
R100	?	?	Broadcom BCM4710@125	16	4	Broadcom	b/g	1	-	-	4 LAN 1 WAN	5	eq As W

Motorola

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	c
<u>WE800G</u>	v1	ACQWE800G	Broadcom BCM4702@125	16	4	Broadcom	b/g	1	?	-	1 L
<u>WR850G</u>	v1	ACQWR850G	Broadcom BCM4702@125	16	4	Broadcom	b/g	1	-	-	4 L 1 V
<u>WR850G</u>	v2	ACQWR850GV2	Broadcom BCM4712@200	16	4	Broadcom	b/g	-	?	?	4 L 1 V
<u>WR850G</u>	v3	ACQWR850GV2	Broadcom BCM4712@200	16	4	Broadcom	b/g	-	?	?	4 L 1 V
<u>WR850GP</u>	?	ACQWR850GV2	Broadcom BCM4712@200	16	4	Broadcom	b/g	-	1	1	'

Supported_Devices

MSI

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
RG70A		U2M-SR97908003	Ralink RT3052F@384	32	4	Ralink	b/g/n	-	1	no	4 LAN 1 WAN

MTN Electronics

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]
MT-WR855N	?	?	Ralink RT3052F@384	32	4	Ralink	b/g/n	-	1	no	4 LAN 1 WAN	9V/1A

NewMedia

Model	H.W. rev	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	Power Input [V]	Special Features Note
Dual A/B/G Router	-	Xscale IXP425@266	32	8	-	depends on card	2	-	?	4 LAN 1 WAN	-	5	= Available

NetComm

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
-------	----------	--------	----------------------------	----------	------------	--------------	------------------------	----------	-------------	-----------	-----------------

Supported_Devices

NP800N	-	U2M-SR97908001	Ralink RT2880F@266	16	4	1	b/g/n , 2 antenna	-	1	?	4 LAN 1 WA
NP801N	-	U2M-SR97908001	Ralink RT2880F@266	16	4	1	b/g/n , 3 antenna	-	1	?	4 LAN 1 WA
NP802N	-	U2M-SR97908002	Ralink RT2880F@266	32	4	1	b/g/n	-	1	?	4 GB LAN 1 GB WA
NP803N	-	U2M-SR97908005	Ralink RT3050F@320	16	4	1	b/g/n	-	1	?	4 LAN 1 WA
NP804N	-	U2M-SR97908003	Ralink RT3052F@384	16	4	1	b/g/n	-	1	?	4 LAN 1 WA

NETCORE

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]
NW618	PB20		Broadcom BCM5354@240	16	4	Broadcom	b/g	-	on board	on board	4 LAN 1 WAN	9V/0.7A

Netgear

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	J
AC1450	v1	PY313200227	Broadcom BCM4708A0@800	256?	128	BCM4360 + BCM4331	a/c 975 b/g/n 450		1	
EX6200	v1	PY313200230	Broadcom BCM4708A0@800	128	8	BCM4352 + BCM43217	a/c 900 b/g/n 300	-	1	1

Supported_Devices

R6200	v1	PY312100189	Broadcom BCM4718A1	128	16	BCM4352 + SOC	a/c 900 b/g/n 300	-	1	1
R6200	v2	PY312400218	Broadcom BCM47081A0@800	256	128	BCM4360 + BCM43217	a/c 1300 b/g/n 300	-	1	1
R6250	v1	PY312400219	Broadcom BCM4708A0@800	256	128	BCM4360 + BCM43217	a/c 1300 b/g/n 300	-	1	1
R6300	v1	PY312100188	Broadcom BCM4706@600	128	128	BCM4360 + BCM4331	a/c 1300 b/g/n 450	-	1	1
R6300	v2	PY313200227	Broadcom BCM4708A0@800	256	128	BCM4360 + BCM4331	a/c 1300 b/g/n 450	-	1	1
R7000	v1	PY313200233	Broadcom BCM4709A0@1000	256	128	BCM4360 x2	a/c 1300 b/g/n 600	-	1	1
<u>WG302</u>	v1	PY3WG302	Xscale IXP422BB@266	16	8	Atheros	b/g @ 20dbm	1	1	?
<u>WG302</u>	v2	PY306100027	Xscale IXP420@266	16	8	Atheros	b/g @ 20dbm	1	1	?
<u>WG602</u>	v3	PY3WG602V3	Broadcom BCM5350@200	8	2	Broadcom	b/g	-	1	?
<u>WG602</u>	v4	PY3WG602V4	Broadcom BCM5354@240	8	2	Broadcom	b/g	-	1	?
<u>WGR614</u>	<u>v8.0</u>	PY306400057	Broadcom BCM5354@240	16	4	Broadcom	b/g	-	1	1
<u>WGR614L</u>	<u>L</u>	PY306400057	Broadcom BCM5354@240	16	4	Broadcom	b/g	-	1	1
<u>WGR614</u>	<u>WW</u>	PY306400057	Broadcom BCM5354@240	16	4	Broadcom	b/g	-	1	?

Supported_Devices

<u>WGR826V</u>	-	PY3WGR826V	Xscale IXP425@266	32	16	Ralink RT2500 (must be replaced)	b/g	1	1	1
<u>WGT624</u>	v1	PY3WGR614V2	Atheros AR2312A@180?	16	4	Atheros AR5001 AP	b/g	-	1	1
<u>WGT624</u>	v2	PY3WGR614V3	Atheros AR2312A@180?	16	4	Atheros AR5001 AP	b/g	-	1	1
<u>WGT624</u>	v4	PY307100060	Atheros AR2318@180	16	4	Atheros	b/g	-	1	-
<u>WN604</u>	v2	PY309300122	Atheros AR7240@400	32	4	Atheros AR9285	b/g/n 1x1:1	-	1	1
<u>WNDR3300</u>	v1	PY307300072	Broadcom BCM4704@264	16	4	Broadcom	a/b/g/n Dual Radio	-	yes	n
<u>WNDR3400</u>	-	PY309300116	Broadcom BCM4718A1@480	64	8	Broadcom	a/b/g/n Dual Radio	-	yes	y
<u>WNDR3400</u>	v2	PY311100156	Broadcom BCM5358U	64	8	SOC + Broadcom BCM43236 dbus	a/b/g/n Dual Radio	-	yes	y
<u>WNDR3700</u> <u>WNDR37AV</u>	v1	PY308300092	Atheros AR7161@680	64	8	AR9220 + AR9223	a/n 2x2:2 b/g/n 2x2:2	-	1	1
<u>WNDR3700</u> <u>WNDR37AV</u>	v2	PY308300092	Atheros AR7161@680	64	16	AR9220 + AR9223	a/n 2x2:2 b/g/n 2x2:2	-	1	1
<u>WNDR3700</u>	v3	PY311200166	Broadcom BCM4718A@480	64	8	SOC + BCM 4331	a/b/g/n Dual Radio	-	1	1
<u>WNDR3700</u>	v4	PY312100186	Atheros AR9344@560	128	128	SOC + AR9582	b/g/n 2x2:2 a/n 2x2:2	-	1	1
<u>WNDR3800</u> <u>WNDR38AV</u>		PY308300092	Atheros AR7161@680	128	16	AR9220 + AR9223	a/n 2x2:2 b/g/n 2x2:2	-	1	1

Supported_Devices

<u>WNDR4000</u>	v1	PY310400144	Broadcom BCM4718@480	64	8	SOC + BCM4331	a/b/g/n Dual radio	-	1	1
WNDR4300	v1	PY312100187	Atheros AR9344@560	128	128	SOC + AR9580	b/g/n 2x2:2 a/n 3x3:3	-	1	1
<u>WNDR4500</u>	v1	PY311200162	Broadcom BCM4706@600	128	128	BCM4331 x2	a/n 450 b/g/n 450	-	1	1
WNDR4500	v2	PY312300207	Broadcom BCM4706@600	128	128	BCM4331 x2	a/n 450 b/g/n 450	-	1	1
WNDR4700	v1	PY311400179	Applied Micro APM82181	256	128	AR9381 + AR9380	a/n 3x3:3 b/g/n 3x3:3	-	1	1
<u>WNR834B</u>	v1	PY306100032	Broadcom BCM4704@264	16	4	Broadcom	b/g/n	-	yes	n
<u>WNR834B</u>	v2	PY307100061	Broadcom BCM4704@264	16	4	Broadcom	b/g/n	-	1	1
<u>WNR1000</u>	v1	PY308400094	Atheros AR9130@400	32	4	Atheros AR9102	b/g/n 2x2:2	-	1	1
<u>WNR1000</u>	v2	PY309300122	Atheros AR7240@400	32	4	Atheros AR9285	b/g/n 1x1:1	-	1	1
<u>WNR2000</u>	v2	PY309100105	Broadcom BCM4716B0@300	32	4	Broadcom	b/g/n	-	1	1
<u>WNR2000</u>	v3	PY310200135	Atheros AR7241@360	32	4	Atheros AR9287	b/g/n 2x2:2	-	1	1
<u>WNR2200</u>	v1	PY310200131	Atheros AR7241@400	64	8	Atheros AR9287	b/g/n 2x2:2	-	1	1
<u>WNR3500</u>	v2	PY308400093	Broadcom BCM4718A@480	32	4	Broadcom	b/g/n	-	-	-
WNR3500L	v1	PY308400093	Broadcom BCM4718A@480	64	8	Broadcom	b/g/n	-	-	-

Supported_Devices

WNR3500L	v2	PY310400153	Broadcom BCM5357@480	128	128	Broadcom	b/g/n	-	-	-
----------	----	-------------	-------------------------	-----	-----	----------	-------	---	---	---

Nokia

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]	Port
IP110	-	-	Geode@300	64	5GB HDD	-	-	-	2	?	3 LAN WAN	5V 5A	II
IP120	-	-	Geode@300	128	5GB HDD	-	-	-	2	?	3 LAN WAN	5V 5A	II
IP130	-	-	Geode@300	256	5GB HDD	-	-	-	2	?	3 LAN WAN	5V 5A	II
IP330	-	-	x86@166-550	64	4-8GB HDD	-	-	-	1	?	3 LAN WAN	110-230V	II S sl

OpenMesh

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE
OM1P	-	WT8-OM1P	Atheros AR2315A@180	32	8	Atheros	b/g	-	1	?	1 WAN or LAN	-

Supported_Devices

OpenRB

Model	H.W. rev	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	Power Input [V]
<u>OpenRB Light</u>	-	IBM PPC405@266-333	32	8	-	depends on card	1	1	2	2 LAN	passive PoE	5-40V
<u>OpenRB Medium</u>	-	IBM PPC405@266-333	32-64	8	-	depends on card	2	1	2	2 LAN	passive PoE	5-40V

OSBRIDGE

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Power Input [V]
2Ni (V/H/Ex)	-	?	Atheros AR7240@400	32	4	Atheros AR9285	b/g/n 1x1:1	-	?	?	1 L W
<u>24XLG</u>	-	?	Atheros AR2316@ ?	16	4	1	b/g (Atheros AR2316)	-	?	?	1 L W
<u>24XLGi</u>	-	?	Atheros AR2316@ ?	16	4	1	b/g (Atheros AR2316)	-	?	?	1 L W
<u>5G(-HP)</u>	-	?	Xscale IXP425@533	64	4	2	a (Atheros AR5006XS)	-	?	?	1 L W
<u>5Gi(-HP)</u>	-	?	Xscale IXP422@266	32	4	1	a (Atheros AR5006XS)	-	?	?	1 L W
<u>5GL(-HP)</u>	-	?	Xscale IXP422@266	32	4	1	a (Atheros AR5006XS)	-	?	?	1 L W

Supported_Devices

<u>5GXt(-HP)</u>	-	?	Xscale IXP425@533	64	4	2	a (Atheros AR5006XS)	-	?	?	1 L W
<u>5GXt-HP-N</u>	-	?	Xscale IXP425@533	64	4	2	a (Atheros AR5006XS)	-	?	?	1 L W
5Ni	-	?	Atheros AR9130@400	32	4	Atheros AR9104	a/h/n 2x2:2	-	?	?	1 L W
5NXi	-	?	Atheros AR9130@400	32	4	Atheros AR9104@23dBm	a/h/n 2x2:2	-	?	?	1 L W
<u>5Si</u>	-	-	Atheros AR2313@180	16	4	1	a/h @ 24dbm	-	1	?	1 L
<u>5GXi(-HP)</u>	-	?	Infineon ADM5120@175	16	2	1	a @ 24dBm (Atheros AR5006XS)	-	?	?	1 L W
<u>5XLi</u>	-	?	Infineon ADM5120@175	16	2	1	a @ 18dBm (Atheros AR5006XS)	-	?	?	1 L W

Ovislink

- [see Airlive](#)

PC-Engines

Model	H.W. rev	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	P I
<u>Alix</u>	-	Geode LX@433-500	128-256	depends on cf card	depends on card	depends on card	1-2	1	?	1-3	yes	7-

Supported_Devices

<u>Wrap</u>	-	Geode SC1100@233-266	64-128	depends on cf card	depends on card	depends on card	1-2	1	?	1-3	yes	7-
<u>APU</u>	-	AMD T40E@1GHz	2-4GB	depends on cf card or m-SATA	depends on card	depends on card	2	1	?	3 Gig Ethernet	-	12

Planex aka PCI

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port
GW-MF54G2	?	MQ4WAP2102	Atheros AR2317@180	16	4	Atheros	b/g	?	?	?
MZK-W04NU	v1.0	SJ9-MZKW04NU	Atheros AR9132@400	32MB	8 MB	Atheros AR9103	b/g/n 2x3:2	-	1	1
MZK-W300NH	v1.0	SJ9-MZKW300NH	Atheros AR9130@400	32MB	8 MB	Atheros AR9102	b/g/n 2x2:2	-	1	1

Ravo

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
<u>W54-RT</u>	-	H8N-RT210W	Broadcom BCM4710@125	16	4	Broadcom	b/g	1	1	1	4 LAN 1 WAN

Supported_Devices

RayTalk

Model	H.W. rev	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	Power Input [V]
<u>MHAN-X1</u>	-	Xscale IXP425@533	64	16	-	2x a/b/g/h	2 or 4	2?	1?	2 LAN	802.3af?	?
<u>MHAN-X3</u>	-	Xscale IXP425@533	64	16	-	2x a/b/g/h	2 or 4	2?	1?	2 LAN	802.3af?	?

Repotec

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]
<u>RP-WR5422</u>	?	?	Ralink RT3052F@380	32	4	Ralink	b/g/n	-	1	-	4 LAN 1 WAN	?

RFNet Technologies

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE
AP1062	-	PXPAP1062	Atheros AR2315@180	16	4	Atheros	b/g	-	1	1	1 LAN WAN	yes

Rosewill

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port
RNX-EasyN4	-	U2M-SR97908003		32	4	Ralink	b/g/n	-	1

Supported_Devices

			Ralink RT3052@384								
RNX-EasyN400	-	U2M-SR97908005	Ralink RT3050@320	16	4	Ralink	b/g/n	-	1		
RNX-GX4	-	W6RRNX-GX4	Broadcom BCM5354@240	16	4	Broadcom	b/g	-	1		
RNX-N150RT		TE7WR741NX	Atheros AR7240@400	32	4	Atheros AR9285@17dBm	b/g/n 1x1:1	-	1		
RNX-N300RT		TE7WR841NXV7	Atheros AR7241@400	32	4	Atheros AR9287@20dBm	b/g/n 2x2:2	-	1		

Ruckus

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	P I [
VF2111	?	HED-FON2100	Atheros AR2315@180	16	8	Atheros	b/g	-	1	?	1 WAN	12 12

Senao / EnGenius

Model	FCC Id	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port
EAP-350	U2M-?	Atheros AR7242@400	32	4	Atheros AR9283@29dbm	b/g/n 2x2:2	-	?

Supported_Devices

EAP-600	U2M-?	Atheros AR9344@600	64	8	SOC + Atheros AR9382	b/g/n 2T2R@26dbm a/n 2T2R@29dbm	-	?
<u>EAP-3660 / M36</u>	U2M-AP36600801	Atheros AR2316@180	16	4	1	b/g@27dbm	-	1
EAP-9550	U2M-AP9550	Ralink RT3052@380	32	4	1	b/g/n@18dbm	-	1
ECB-3500	-	Atheros AR2315@180	32	8	1	b/g@27dbm	-	?
ECB-9500	U2M-CB97508001	Ralink RT2880@266	32	8	1	b/g	-	1
ECB-9750	U2M-CB97508001	Ralink RT2880@266	32	8	1	b/g	-	1
EOA-3650	-	Atheros AR2315@180	32	8	1	b/g @ 28dbm	-	?
<u>EOA-8670</u>	U2M-OA86708001	Xscale IXP425@533	64	16	-	2x a/b/g/h	2	2
<u>EOC-1630</u>	-	Atheros AR2315@180	32	8	1	b/g @ 23dbm	-	?
<u>EOC-1650</u>	U2M-OC1650	Atheros AR2315@180	32	8	1	b/g @ 23dbm	-	?
<u>EOC-2610 / M2000</u>	U2M-OC26100801	Atheros AR2315@180	32	8	1	b/g @ 27dbm	-	1
EOC-2611	-	Atheros AR2316@180	32	8	1	b/g @ 28dbm	-	1
EOC-5510	-	Atheros AR2313@180	32	8	Atheros AR5112	a/h @ 28dbm	-	1

Supported_Devices

<u>EOC-5610 / M5000</u>	U2M-OC5610	Atheros AR2313@180	32	8	Atheros AR5112	a/b/g/h @ 23dbm	-	1	
EOC-5611	-	Atheros AR2313@180	32	8	Atheros AR5112	a/b/g/h @ 27dbm	-	1	
<u>EOM-8670</u>	U2M-OA86708001	Xscale IXP425@533	64	16	-	2x a/b/g/h	2	2	1
<u>EOP-8670 / NOP-8670</u>	U2M-OA86708001	Xscale IXP425@533	64-128	16	-	depends on card	2	2	1
<u>EOR-7550</u>	U2M-OR7750801	Ralink RT2880@266	32	8	-	a/b/g/h + b/g/n	2	2	1
ESR-6650	U2M-SR97908005	Ralink RT3050@384	32	4	SOC	b/g/n	-	1	
ESR-6670		Ralink RT3052F@384	16	4	SOC	b/g/n	-	1	
ESR-6670A		Ralink RT3052F@384	32	4	SOC	b/g/n	-	1	
ESR-9750	U2M-SR97908001	Ralink RT2880@266	16	4	Ralink RT2820L	b/g/n 2T3R	-	1	
ESR-9750A	U2M-SR97908002	Ralink RT2880@266	16	4	Ralink RT2820L	b/g/n 2T3R	-	1	
ESR-9750B		Ralink RT2880@266	32	4	Ralink RT2820L	b/g/n 2T3R	-	1	

Supported_Devices

ESR-9750G	U2M-SR97908002	Ralink RT2880@266	32	4	Ralink RT2820L	b/g/n 2T3R	-	1
<u>ESR-9752</u>	U2M-SR97908003	Ralink RT3052@384	16	4	SOC	b/g/n	-	1
<u>ESR-9752B</u>	U2M-SR97908003	Ralink RT3052@384	32	4	SOC	b/g/n	-	1
ESR-9753	U2M-SR97908005	Ralink RT3050F@320	16	4	SOC	b/g/n	-	1
ESR-9850	U2M-?	Ralink RT3052F@384	32	4	SOC	b/g/n	-	1
ETR-9330	U2M-TR9350	Ralink RT3052@384	32	4	SOC	b/g/n	-	1
ETR-9350	U2M-TR9350	Ralink RT3052@384	32	4	SOC	b/g/n	-	1
ETR-9360	U2M-TR9360	Ralink RT3050F@320	32	4	SOC	b/g/n	-	1

Siemens

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port
<u>Gigaset SE505</u>	v1	H8NRT210W	Broadcom BCM4710@125	16	4	Broadcom	b/g	-	1	1
<u>Gigaset SE505</u>	v2	H8NRT480W		8	4		b/g	-	yes	yes

Supported_Devices

			Broadcom BCM4712@200			Broadcom onboard				
<u>Gigaset_SE505</u>	v3	?	Broadcom BCM4712@200	8	4	Broadcom	b/g	-	yes	yes
<u>Gigaset_SX550</u>	?	?	Broadcom BCM4710@125	16	4	Broadcom	b/g	1	?	?
<u>Gigaset_SX550i</u>	?	?	Broadcom BCM4710@125	16	4	Broadcom	b/g	1	?	?

Sitecom

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JT p
<u>WL105b</u>	-	MXF-A910910AB	Broadcom BCM4702@125	16	4	Broadcom	b/g	1	-	yes
<u>WL111</u>	-	?	Broadcom BCM4702@125	16	4	Broadcom BCM4306KFB	b/g	1	?	1
WL303	-	U2M-SR97908001	Ralink RT2880F@266	16	4	1	b/g/n	-	1	?
WL306	-	U2M-SR97908002	Ralink	16	4	1	b/g/n	-	1	?

Supported_Devices

			RT2880F@266							
WL312	-	U2M-SR97908001	Ralink RT2880F@266	16	4	1	b/g/n	-	1	?
WL326	-		Ralink RT3052@384	16	4	1	b/g/n	-	1	?
WL328	-	U2M-SR7750	Ralink RT3052@384 + RT2880F@266	32 + 16	8 + 2	1	a/b/g/n	-	1	?
WL340	v2	U2M-SR97908005	Ralink RT3050@320	16	4	1	b/g/n	-	1	?
WL341	v2	U2M-SR97908003	Ralink RT3052@384	16	4	1	b/g/n	-	1	?
WL342	v2	U2M-SR97908003	Ralink RT3052@384	16	4	1	b/g/n	-	1	?
WL351	-	U2M-SR9850	Ralink RT3052@384	32	4	1	b/g/n	-	1	?
WL357	-	U2M-TR9350	Ralink RT3052@384	32	4	1	b/g/n	-	1	?
WL361	-	U2M-TR9360	Ralink RT3050@320	32	8	1	b/g/n	-	1	?
WL368	-	U2M-SR9850	Ralink RT3052@384	32	4	1	b/g/n	-	1	?
WLR-4000	v1	?	Ralink	32	?	1	b/g/n	-	1	1

Supported_Devices

Snapgear

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	Power Input [V/A]
SG565	-	-	Xscale IXP420@266	64	8	Ralink 2560 (must be replaced)	b/g	1	1	1	4 LAN 1 WAN	-	?

SOEKRIS Engineering

Model	H.W. rev	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE
<u>net4801-XX</u>	-	Geode SC1100@233-266	32-256	depends on cf or hdd	-	depends on card	1	2	?	3	-
<u>net4826-XX</u>	-	Geode SC1100@233-266	32-256	depends on cf or hdd	-	depends on card	1-2	1	?	1	802.11
<u>net5501-XX</u>	-	Geode LX@433-500	128-1024	depends on cf or hdd	-	depends on card	1	2	?	1-4	-

SparkLAN

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]
<u>WAPD-170AG</u>	2	MXF-A950806AG		64	16	-	

Supported_Devices

			Xscale IXP425@533								depends on card	
<u>WAPD-182N</u>	-	-	Atheros AR7161@680	64	8	-					depends on card	3
<u>WX6615</u>	PCB WX5525R_V02	MXF-R920220G	Broadcom BCM4702@125	16	4	Broadcom BCM4306KFB	b/g					1
<u>WX 6615 GT</u>	-	MXF-R930116G	Broadcom BCM4712@200	16	4	Broadcom BCM2050KML	b/g					1
WX7615A	-	RYK-7615A	Atheros AR5312@220	16	4	Atheros	a/b/g/h					-
<u>WX 7800A</u>	-	RYK-7800A	Atheros AR5312@220	16	4	Atheros	a/b/g/h					-

Straight Core

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE
GWA-627EX	-	-	Atheros AR2313A@180	16	4	Atheros	a/h	-	1	1	1 LAN WAN	yes

Technaxx

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]	Spec Featu Not
Router 150	?	?	Ralink RT3052@380	32	4	-	b/g/n	-	-	-	4 LAN	?	?

Supported_Devices

											1 WAN		
Router 300	?	?	Ralink RT3052@380	32	4	-	b/g/n	-	-	-	4 LAN 1 WAN	?	?

Technician

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	Power Input [V/A]
WAR-54GAT	v2	?	Atheros AR2317@180	16	4	-	b/g	1	?	?	4 LAN 1 WAN	9V 0.8A

Tonze

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE
<u>AP-120</u>	-	?	Infineon ADM5120@175	32	2(4)	-	depends on card	1	?	?	1 LAN?	?
<u>AP-425</u>	-	?	Xscale IXP425@533	64	8	-	depends on card	2	1	1	2 LAN	yes
<u>AW-6660]</u>	-	?	Atheros AR5312@220	16?	4?	Atheros	a/b/g/h	-	1	1	1 LAN	?

Supported_Devices

Toshiba

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	Power Input [V]
<u>Magnia SG-20</u>	?	?	Celeron @ 566	64	depends on hdd / cf	-	depends on card	1+1 PC Card-Slot	?	?	8 LAN 1 WAN	yes	230

TP-Link

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]
Archer C5	1.x	TE7C5	Qualcomm/Atheros QCA9558@720	128	16	SOC + QCA9880v2	b/g/n 3x3:3 an/ac 3x3:3
Archer C7	2.x	TE7C7V2	Qualcomm/Atheros QCA9558@720	128	16	SOC + Atheros QCA9880	b/g/n 3x3:3 an/ac 3x3:3
Archer C8	1.x	TE7C8	BCM4708@800	128	16	Broadcom BCM4360 + BCM4331	an/ac 1300 b/g/n 450
Archer C9	1.x	TE7C9	BCM4709@1000	128	16	Broadcom BCM4360 x 2	an/ac 1300 b/g/n 600
MR11U	1.x, 2.x	- (China version)	Atheros AR9331@400	32	4	SOC	b/g/n 1x1:1
MR12U	1.x	- (China version)	Atheros AR9331@400	32	4	SOC	b/g/n 1x1:1
MR13U	1.x	- (China version)	Atheros AR9331@400	32	4	SOC	b/g/n 1x1:1
MR3020	1.x	TE7MR3020	Atheros AR9331@400	32	4	SOC	b/g/n 1x1:1
MR3040	1.x	TE7MR3040V1	Atheros AR9331@400	32	4	SOC	

Supported_Devices

							b/g/n 1x1:1
<u>MR3220</u>	1.x	TE7MR3220	Atheros AR7241@400	32	4	Atheros AR9285@20dBm	b/g/n 1x1:1
MR3220	2.x	TE7MR3220V2	Atheros AR9331@400	32	4	SOC	b/g/n 1x1:1
<u>MR3420</u>	1.x	TE7MR3420	Atheros AR7241@400	32	4	Atheros AR9287@23dBm	b/g/n 2x2:2
MR3420	2.x	TE7MR3420V2	Atheros AR9341@535	32	4	SOC	b/g/n 2x2:2
WA701N(D)	1.x	TE7WA701ND	Atheros AR7240@400	32	4	Atheros AR9285@20dBm	b/g/n 1x1:1
WA701N(D)	2.x	TE7WA701NDV2	Atheros AR9331@400	32	4	SOC	b/g/n 1x1:1
WA730RE	1.x	TE7WA730RE	Atheros AR7240@400	32	4	Atheros AR9285@20dBm	b/g/n 1x1:1
WA730RE	2.x	TE7WA730REV2	Atheros AR9331@400	32	4	SOC	b/g/n 1x1:1
<u>WA801N(D)</u>	1.x	TE7WA801ND	Atheros AR7240@400	32	4	Atheros AR9283	b/g/n 2x2:2
WA801N(D)	2.x	TE7WA801NDV2	Atheros AR9341@535	32	4	SOC	b/g/n 2x2:2
WA830RE	1.x	TE7WA830RE	Atheros AR7240@400	32	4	Atheros AR9283@20dBm	b/g/n 2x2:2
WA830RE	2.x	TE7WA830REV2	Atheros AR9341@535	32	4	SOC	b/g/n 2x2:2
WA850RE	1.x??	TE7WA850RE	Atheros AR9341@535	32	4	SOC@20dBm	b/g/n 2x2:2
<u>WA901N(D)</u>	1.x	-	Atheros AR7240@400	32	4	Atheros AR9285@20dBm	b/g/n 1x1:1

Supported_Devices

<u>WA901N(D)</u>	2.x	TE7WA901ND	Atheros AR9132@400	32	4	Atheros AR9103@20dBm	b/g/n 2x3:3
<u>WA7210N</u>	v2.x	TE7WA7210N??	Atheros AR9331@400	32	4	SOC	b/g/n 1x1:1
<u>WA7510N</u>	v1.x	TE7WA7510N	Atheros AR7240@400	32	4	Atheros AR9280@15dBm	a/n 1x1:1
WDR3500	1.x	TE7WDR3500	Atheros AR9344@560	128	8	SOC + Atheros AR9582	b/g/n 2x2:2 a/n 2x2:2
WDR3600	1.x	TE7WDR3600	Atheros AR9344@560	128	8	SOC + Atheros AR9582	b/g/n 2x2:2 a/n 2x2:2
WDR4300	1.x	TE7WDR4300	Atheros AR9344@560	128	8	SOC + Atheros AR9580	b/g/n 2x2:2 a/n 3x3:3
WDR4310	1.x	- (China version)	Atheros AR9344@560	128	8	SOC + Atheros AR9580	b/g/n 2x2:2 a/n 3x3:3
WDR4320	1.x	- (China version)	Atheros AR9344@560	128	8	SOC + Atheros AR9580	b/g/n 2x2:2 a/n 3x3:3
WDR4900	1.x	TE7WDR4900	Freescale P1014@800	128	16	Atheros AR9580 + AR9381	b/g/n 3x3:3 a/n 3x3:3
WDR4900	2.x	- (China version)	Qualcomm/Atheros QCA9558@720	128	8	SOC + Atheros AR9580	b/g/n 3x3:3 a/n 3x3:3
WR703N	1.x	- (China version)	Atheros AR9331@400	32	4	SOC	b/g/n 1x1:1
WR710N	1.x Worldwide		Atheros AR9331@400	32	8	SOC	b/g/n 1x1:1
<u>WR740N</u>	1.x	TE7WR740N	Atheros AR7240@400	32	4	Atheros AR9285@20dBm	b/g/n 1x1:1
<u>WR740N</u>	2.x	TE7WR740N	Atheros AR7240@400	32	4	Atheros AR9285@20dBm	b/g/n 1x1:1
<u>WR740N</u>	3.x	TE7WR740N	Atheros AR7240@400	32	4	Atheros AR9285@20dBm	b/g/n 1x1:1

Supported_Devices

<u>WR740N</u>	4.x		Atheros AR9331@400	32	4	SOC	b/g/n 1x2:1
<u>WR741N(D)</u>	1.x, 2.x	TE7WR741NX	Atheros AR7240@400	32	4	Atheros AR9285@17dBm	b/g/n 1x1:1
WR741ND	4.x	TE7WR741NDV4	Atheros AR9331@400	32	4	SOC	b/g/n 1x2:1
<u>WR743N(D)</u>	1.x	TE7WR743ND	Atheros AR7240@400	32	4	Atheros AR9285@17dBm	b/g/n 1x1:1
WR743N(D)	2.x	TE7WR743NDV2	Atheros AR9331@400	32	4	SOC	b/g/n 1x1:1
WR800N	1.x	Chinese version ONLY	Atheros AR9341@535	32	4	SOC@20dBm	b/g/n 2x2:2
WR840N	1.x	Chinese version ONLY	Atheros AR7241@400	32	4	Atheros AR9287@20dBm	b/g/n 2x2:2
<u>WR841N(D)</u>	3.x	TE7WR841ND	Atheros AR9132@400	32	4	Atheros AR9103@20dBm	b/g/n 2x3:3
<u>WR841N(D)</u>	5.x	TE7WR841NXV5	Atheros AR7240@400	32	4	Atheros AR9283@20dBm	b/g/n 2x2:2
<u>WR841N(D)</u>	7.x	TE7WR841NXV7	Atheros AR7241@400	32	4	Atheros AR9287@20dBm	b/g/n 2x2:2
<u>WR841N(D)</u>	8.x	TE7WR841NXV8	Atheros AR9341@535	32	4	SOC@20dBm	b/g/n 2x2:2
WR841N(D)	9.x	TE7WR841NXV9	QCA9533@550	32	4	SOC@20dBm	b/g/n 2x2:2
WR842N(D)	1.x	TE7WR842ND	Atheros AR7241@400	32	8	Atheros AR9287@20dBm	b/g/n 2x2:2
WR842ND	2.x	TE7WR842NDV2	Atheros AR9341@535	32	8	SOC@20dBm	b/g/n 2x2:2
<u>WR940N</u>	1.x	TE7WR940N	Atheros AR9132@400	32	4	Atheros AR9103@20dBm	b/g/n 2x3:3
<u>WR940N</u>	v2	TE7WR941NXV5	Atheros AR9341@535	32	4	SOC@20dBm	b/g/n 2x2:2

Supported_Devices

<u>WR941N(D)</u>	1.x, 2.x, 3.x	TE7WR941NX	Atheros AR9132@400	32	4	Atheros AR9103@20dBm	b/g/n 2x3:3
<u>WR941N(D)</u>	4.x, "old" 5.x	TE7WR941NXV4	Atheros AR7241@400	32	4	Atheros AR9103@20dBm	b/g/n 2x3:3
<u>WR941N(D)</u>	"new" 5.x	TE7WR941NXV5	Atheros AR9341@535	32	4	SOC@20dBm	b/g/n 2x2:2
<u>WR941N(D)</u>	6.x	TE7WR941NXV6	Atheros AR9344@560	32	4	Atheros AR9381@20dBm	b/g/n 3x3:3
<u>WR1043N(D)</u>	1.x	TE7WR1043NX	Atheros AR9132@400	32	8	Atheros AR9103	b/g/n 2x3:3
WR1043ND	2.x	-	Qualcomm/Atheros QCA9558-AT4A@720	64	8	SOC	b/g/n 3x3:3
WR2543ND	1.x	TE7WR2543N	Atheros AR7242@400	64	8	Atheros AR9380	a/b/g/n 3x3:3

Tranzeo

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	Power Input [V]
ER1000 (HG)	?	?	Xscale IXP425@533	64	16	-	1x b/g @ 26dBm	2	1	Yes	1 LAN WAN	yes	9- 48

Supported_Devices

TRENDnet

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mir PC
TEW-410APB+	-	MXF-A930209G	Broadcom BCM4712KPB	8	2	Broadcom BCM2050KML	b/g	-
<u>TEW-411BRP</u>	-	MXF-R920220G	Broadcom BCM4702@125	16	4	Broadcom 4306KFB	b/g	1
<u>TEW-511BRP</u>	-	RYK-7615A	Atheros AR5312@220	16	4	Atheros AR2112 + AR5112	a/b/g/h	-
<u>TEW-632BRP</u>	A1.xR	S9ZTEW632BRP	Atheros AR9130@400	32	4	Atheros AR9102	b/g/n 2x2:2	-
<u>TEW-652BRP</u>	V1.xR	S9ZTEW652BRP	Atheros AR9130@400	32	4	Atheros AR9102	b/g/n 2x2:2	-
<u>TEW-653AP</u>	?	?	Ralink RT3052@380	32	4	Ralink 2x2 MIMO	b/g/n @ 18dBm	-
TEW-654TR	A1	S9ZTEW654TR	Ralink RT3052@380	32	4	Ralink	b/g/n	-

Supported_Devices

<u>TEW-672GR</u>	V1.0R	S9ZTEW672GR	Ralink RT2880@266	32	4	Ralink RT2850L	b/g/n	-
TEW-673GRU	V1.0R	XU8TEW673GRU	Atheros AR7161@680	64	8	AR9220 + AR9223	a/n 2x2:2 b/g/n 2x2:2	-
TEW-811DRU	v1	XU8TEW1200AC	BCM47081A0@800	64	8	BCM4352 + BCM43217	a/c 900 b/g/n 300	-
TEW-812DRU	v1	XU8TEW1750AC	BCM4706@600	128	128	BCM4360 + BCM4331	a/c 1300 b/g/n 450	1
TEW-812DRU	v2	XU8TEW1750ACv2	BCM4708A0@800	64	8	BCM4360 + BCM4331	a/c 1300 b/g/n 450	1
TEW-818DRU	v1	XU8TEW818DRU	BCM4708A0@800	128	16	BCM4360 + BCM4360	a/c 1300 b/g/n 600	-

T&W

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	P I [
ZXV10 H618B/H118B	-	?	Broadcom BCM5354@240	32	16	Broadcom	b/g	-	1	-	4 LAN 1 WAN	12 12
RG100E-AA	-	?	Broadcom BCM5354@240	32	16	Broadcom	b/g	-	1	-	4 LAN 1 WAN	12 12
DI-524SU	E1/E8	?		32	16	Broadcom	b/g	-	1	-		

Supported_Devices

			Broadcom BCM5354@240							4 LAN 1 or 0 WAN	12 12
--	--	--	-------------------------	--	--	--	--	--	--	---------------------------	----------

Ubiquiti

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port
AirGateway M2 HP	-	SWX-?	Atheros AR7240@400	32	8	1	b/g/n @ ?dBm 1T1R	-	1	?
AirGrid M2 HP	-	SWX-M2G	Atheros AR7240@400	32	8	1	b/g/n @ 28dBm 1T1R	-	1	?
AirGrid M5 HP	-	SWX-M5G	Atheros AR7240@400	32	8	1	a/h/n @ 25dBm 1T1R	-	1	?
AirRouter	-	SWX-E2	Atheros AR7240@400	32	8	1	b/g/n @ 19dBm 1T1R	-	1	?
AirWire	-	SWX-M5L	Atheros AR7240@400	32	8	1	a/n @ 23dBm 2T2R	-	1	?
<u>Bullet2 (HP)</u>	-	SWX-B2L	Atheros AR2313@180	16	4	1	b/g @ 20 (30) dbm	-	?	?
<u>Bullet5 (HP)</u>	-	SWX-B5	Atheros AR2313@180	16	4	1	a/h @ 22 (30) dBm	-	?	?
Bullet M2	-	SWX-M2B	Atheros AR7240@400	32	8	1	b/g/n @ 25dBm 1T1R	-	1	?
Bullet M2 Titanium	-	SWX-?	Atheros AR?@400	32	8	1	a/h/n @ 28dBm 1T1R	-	1	?
Bullet M5	-	SWX-M5B	Atheros AR7240@400	32	8	1	a/h/n @ 28dBm 1T1R	-	1	?
	-	SWX-?		32	8	1		-	1	?

Supported_Devices

Bullet M5 Titanium			Atheros AR?@400				a/h/n @ 28dBm 1T1R			
<u>LiteStation2</u>	-	SWX-LS2T	Atheros AR2316@180	16	4	1	b/g @ 400mW	-	1	?
<u>LiteStation5</u>	-	SWX-LS5T	Atheros AR5312@180	16	4	1	a/h @ 400mW	-	1	?
<u>LiteStationSR71</u>	-	-	Atheros AR7161@680	32	8	-	depends on card	1	1	yes
<u>LiteStationX</u>	-	-	Atheros AR7131@300	32	8	-	depends on card	1	1	yes
NanoBeam NBE-M2-400	-	SWX-?	Atheros AR?@560	64	8	1	b/g/n @ 28dBm 2T2R	-	1	?
NanoBeam NBE-M5-16 / NBE-M5-19	-	SWX-?	Atheros AR?@560	64	8	1	b/g/n @ 26dBm 2T2R	-	1	?
NanoBeam NBE-M5-300 / NBE-M5-400	-	SWX-?	Atheros AR?@560	64	8	1	b/g/n @ 26dBm 2T2R	-	1	?
NanoBridge M9	-	SWX-?	Atheros AR7240@400	64	8	1	b/g/n @ 28dBm 2T2R	-	1	?
NanoBridge M2	-	SWX-M2D	Atheros AR7240@400	32	8	1	b/g/n @ 23dBm 2T2R	-	1	?
NanoBridge M3 / M365	-	SWX-?	Atheros AR7240@400	32	8	1	b/g/n @ 25dBm 2T2R	-	1	?
NanoBridge M5	-	SWX-M5D	Atheros AR7240@400	32	8	1	a/h/n @ 22(25)dBm 2T2R	-	1	?
<u>NanoStation2</u>	-	SWX-NS2	Atheros AR2316@180	16	4	1	b/g @ 26dbm	-	1	?
<u>NanoStation3</u>	-	SWX-NS3	Atheros AR2313@180	16	4	1	3GHz @ 24dbm	-	1	?

Supported_Devices

<u>NanoStation5</u>	-	SWX-NS5	Atheros AR2313@180	16	4	1	a/h @ 24dbm	-	1	?
NanoStation M2	-	SWX-M2N	Atheros AR7240@400	32	8	1	b/g/n @ 28dBm 2T2R	-	1	?
NanoStation M365	-	SWX-M365N	Atheros AR7240@400	32	8	1	3GHz @ 25dBm 2T2R	-	1	?
NanoStation M5	-	SWX-M5N	Atheros AR7240@400	32	8	1	a/h/n @ 27dBm 2T2R	-	1	?
<u>NanoStation loco2</u>	-	SWX-L2	Atheros AR2316@180	16	4	1	b/g @ 20dbm	-	1	?
<u>NanoStation loco5</u>	-	SWX-NS5	Atheros AR2313@180	16	4	1	a/h @ 22dbm	-	1	?
NanoStation Loco M2	-	SWX-M2L	Atheros AR7240@400	32	8	1	b/g/n @ 23dBm 2T2R	-	1	?
NanoStation Loco M5	-	SWX-M5LB	Atheros AR7240@400	32	8	1	a/h/n @ 23dBm 2T2R	-	1	?
NanoStation Loco M900	-	SWX-M900L	Atheros AR7240@400	32	8	1	900MHz @ 26dBm 2T2R	-	1	?
<u>MiniStation</u>	-	-	Atheros AR2315@180	16	4	1	b/g @ 26dbm	-	1	?
<u>PicoStation2 (HP)</u>	-	SWX-B2	Atheros AR2315@180	32	8	1	b/g @ 26dbm	-	1	?
<u>PicoStation5</u>	-	-	Atheros AR23?@180	32	8	1	a/h @ ?dbm	-	1	?

Supported_Devices

PicoStation M2 HP	-	-	Atheros AR7240@400	32	8	1	b/g/n @ 27dBm 1T1R	-	1	?
PicoStation M5 HP	-	-	Atheros AR7240@400	32	8	1	a/h/n @ 27dBm 1T1R	-	1	?
PowerAP N	-	-	Atheros AR7240@400	64	8	1	b/g/n @ 23dBm 2T2R	-	1	?
PowerBridge M5	-	SWX-M5P	Atheros AR7240@400	64	8	1	a/n @ 27dBm 2T2R	-	1	?
PowerBridge M10	-	SWX-?	Atheros AR7240@400	64	8	1	10GHz @ 33dBm 2T2R	-	1	?
<u>PowerStation2</u>	-	-	Atheros AR2316@180	16	4	1	b/g @ 400mW	-	1	?
<u>PowerStation2 Ext</u>	-	-	Atheros AR2316@180	16	4	1	b/g @ 400mW	-	1	?
<u>PowerStation5</u>	-	-	Atheros AR2313@180	16	4	1	a/h @ 400mW	-	1	?
<u>PowerStation5 Ext</u>	-	-	Atheros AR2313@180	16	4	1	a/h @ 400mW	-	1	?
Rocket M2	-	SWX-M2	Atheros AR7240@400	64	8	1	b/g/n @ 27dBm 2T2R	-	1	?
Rocket M2 Titanium	-	SWX-?	Atheros AR?@550	128	8	1	b/g/n @ 28dBm 2T2R	-	1	?
Rocket M365	-	SWX-M365	Atheros AR7240@400	64	8	1	3,6GHz @ 20dBm 2T2R	-	1	?
Rocket M5	-	SWX-M5	Atheros AR7240@400	64	8	1	a/h/n @ 27dBm 2T2R	-	1	?

Supported_Devices

Rocket M5 Titanium	-	SWX-?	Atheros AR?@550	128	8	1	b/g/n @ 27dBm 2T2R	-	1	?
<u>RouterStation</u>	-	-	Atheros AR7161@680	64	16	-	depends on card	3	1	yes
<u>RouterStation Pro</u>	-	-	Atheros AR7161@680	128	16	-	depends on card	3	1	yes
UniFi AP	-	SWX-UAP	Atheros AR7240@400	32	8	1	b/g/n @ 20dBm 2T2R	-	1	?
<u>WispStation5</u>	-	SWX-WS5	Atheros AR5312@180	16	4	-	a @ 22dbm	-	1	?

US Robotics

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port
<u>USR5430</u>	Rev 1	MXF-EB921201G	Broadcom BCM4712@200	8	2	Broadcom	b/g	-	?	?
<u>USR5432</u>	-	IXM-APGBR02	Broadcom BCM5350@200	8	2	Broadcom	b/g	-	1	?
<u>USR5441</u>	-	IXM-APGBR02	Broadcom BCM5350@200	8	2	Broadcom	b/g	-	1	?
<u>USR5451</u>	-	IXM-APGBR02	Broadcom BCM5350@200	8	2	Broadcom	b/g	-	1	?
<u>USR5453</u>	-	NHPUSR5453	Atheros AR2313@180	32	8	Atheros	b/g	-	no	1

Supported_Devices

<u>USR5455</u>	-	IXM-APGBR03	Broadcom BCM5354@240	16	4	Broadcom	b/g	-	1	1
<u>USR5461</u>	-	IXM-RTGBR02	Broadcom BCM5350@200	8	2	Broadcom	b/g	-	1	?
<u>USR5465</u>	-	IXM-RTGBR03	Broadcom BCM5354@240	16	4	Broadcom	b/g	-	1	1
USR8200	?	-	Xscale IXP422@266	64	16	-	-	-	1	1
<u>USR805430</u>	?	O7J-GL2454MP -0T	Broadcom BCM4712@200	8	2	Broadcom	b/g	-	?	?

Valemount

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE
<u>Lucaya M1020</u>	-	?	Infineon ADM5120@175	16	4	1	b/g	1	1	1	2 LAN WAN	yes
<u>Lucaya M1023</u>	-	?	Infineon ADM5120@175	16	4	1	a/b/g/h	1	1	1	2 LAN WAN	yes
<u>Lucaya M1208</u>	-	?	Infineon ADM5120@175	32	4	-	b/g	1	1	1	2 LAN WAN	yes

Supported_Devices

<u>Lucaya</u> <u>M1214</u>	-	?	Infineon ADM5120@175	16	4	-	depends on card	1	1	1	2 LAN WAN	yes
<u>Lucaya</u> <u>M1517</u>	-	?	Infineon ADM5120@175	16	4	1	a/h	1	1	1	2 LAN WAN	yes
<u>Lucaya</u> <u>X2000</u>	-	?	Xscale IXP420@266	32	8	-	depends on card	2	1	1	1 LAN	802.3at
<u>Lucaya</u> <u>X4000</u>	-	?	Xscale IXP425@533	64	8	4	a/b/g/h	4	1	1	1 LAN	802.3at
<u>Lucaya</u> <u>X4214</u>	-	?	Xscale IXP425@533	64	8	4	1x b/g 3x a/b/g/h	4	1	1	1 LAN	802.3at
<u>Lucaya</u> <u>X4517</u>	-	?	Xscale IXP425@533	64	8	4	a/b/g/h	4	1	1	1 LAN	802.3at

Supported_Devices

<u>WAR1-CPE</u>	-	?	Infineon ADM5120@175	16	4	-	depends on card	1	1	1	2 LAN WAN	yes
<u>WAR2-MPW144B</u>	-	?	Xscale IXP420@266	32	8	-	depends on card	2	1	1	1 LAN	802.3a
<u>WAR4-MPW188B</u>	-	?	Xscale IXP425@533	64	8	-	depends on card	4	1	1	1 LAN	802.3a

Verizon

- OEM Actiontec

Viewsonic

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	LAN or WLAN
WAPBR-100	-	GSS-VS10407	Broadcom BCM4712@200	8	2	Broadcom	b/g	-	?	?	1 L or W
<u>WR100</u>	-	GSS-VS10276	Broadcom BCM4712@200	8	4	Broadcom	b/g	-	?	yes	4 L 1 W

Supported_Devices

VSCOM

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	Power Inp [V/
<u>Alena</u>	-	-	OpenRISC ARM9@166	64	4	-	-	1	2 + 1 console	?	2 LAN WAN	-	9-30
<u>Alekto (SD/LAN)</u>	-	-	OpenRISC ARM9@166	64	4	(1)	(b/g)	1	2 + 1 console	?	2 LAN WAN	-	9-30

Watchguard

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count
<u>FireboxII</u>	-	-	Pentium MMX @ 200 std	64 + SD-RAM Slot	8	-	depends on card	2 pcmcia, 2 pci	2	-	3 LAN
Firebox Edge X10/X20/X55	-	-	IXP422@266	128	1MB NOR/64MB NAND	-	-	1 mini pci	2	1	6
<u>Firebox X1000</u>	-	-	Socket 370 Celeron SL6C8 [1200] or [1400]	256 PC 133	64mb cf-card	-	-	1 mini pci	1 (mother board has pinout plugin)	-	6

Supported_Devices

for 2)

WiliGear

Model	H.W. rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	PoE	P I [
<u>WBD111</u>	-	?	storlink sl3512 ARM920@300	32	8	-	depends on card	1	1	?	1 LAN	yes	9-
<u>WBD222</u>	-	?	storlink sl3512 ARM920@300	32	8	-	depends on card	2	1	?	2 LAN	yes	9-
<u>WBD500</u>	-	?	Atheros AR2315@180	32	8	1	b/g @ 27dBm	-	1	?	1 LAN	yes	9-
<u>WBD324M</u>	-	?	Xscale IXP425@533	64	16	-	depends on card	4	1	-	2 LAN	yes	12
<u>WBD324S</u>	-	?	Xscale IXP425@533	64	16	-	depends on card	4	1	-	2 LAN	yes	12

WinStars

Model	H.W rev	FCC ID	Platform & Frequency [MHz]	RAM [MB]	Flash [MB]	Wireless NIC	WLAN standard [802.11]	mini PCI	Serial port	JTAG port	Eth. port count	P I [
WS-WN511N1	?	?	Ralink RT3052F@384 ?	16 ?	4 ?	Ralink ?	b/g/n	-	1	no	4 LAN 1 WAN	9V
WS-WN511N2	?	?	Ralink RT3052F@384	16	4	Ralink	b/g/n	-	1	no	4 LAN 1	9V

List of Incompatible Routers

See also [Known incompatible devices](#) for the black list.